

Boston, MA 02110

Figure 1 displays 12 histograms showing the distribution of the number of non-zero elements in the vector x for different values of n (10, 20, 30, 40, 50, 60, 70, 80, 90, 100, 110, 120). The x-axis is labeled 'x' and ranges from 0 to 120. The y-axis is labeled 'count' and ranges from 0 to 100. As n increases, the distribution of x becomes more concentrated around zero, with the peak count increasing significantly.

Signature Samantha Bell
Typed or Printed Name of Person Signing Certificate

```
#define WIN31 // need this to use extended 3.1 functionality
#include <windows.h>

#include <toolhelp.h>

#include "vtools.h"
#include "vc.h"

#ifdef DEBUG_DLG
int ContextTabs[3];
#endif
```

How is one window related to another.


```

    struct
    {
        HMENU hMenu;
        int iEntry;
        int iKeyPos;    // How far down is it not counting separators
    } MenuPop;

    struct
    {
        HMENU hMenu;    // Handle of the menu
        WORD id;    // Item ID
        LPSTR szName;    // Alias name from Lang
    } Menu;

    struct
    {
        HMENU hMenu;
        WORD id;    // Item ID
    } Acc;

    struct
    {
        PSTR szTitle;    // Title
        PSTR szFile;    // Command string
    } PMItem;    // PMItem string for CON_LAUNCH

    LPMACRO pMacro;    // Macro from language
} u;

struct tagCONTEXTITEM * pciNext;    // Next item in the list.

} CONTEXTITEM;

/*-----
| Scroll bar types.
|
*/
#define SCRLS_HORZ (0x8000)
#define SCRLS_WIN (0x4000)
#define SCRLS_MDI (0x2000)
#define SCRLS_ACT (~(SCRLS_HORZ | SCRLS_WIN | SCRLS_MDI))

/*-----
| Scroll present mask
|
*/
#define SCRLM_HORZ (0x0001)    // Is horz scroll present
#define SCRLM_VERT (0x0002)    // Is vert scroll present
#define SCRLM_HMDI (0x0004)    // Is MDI Workspace scroll present
#define SCRLM_VMDI (0x0008)

```

```

/*-----
|
| Context List.
|
*/
_LOCAL CONTEXTITEM * pciFirst = NULL;
_LOCAL CONTEXTITEM * pciLast = NULL;

_LOCAL unsigned iCheckSum = (UINT)-1;    // Keep a check sum of the context.

_LOCAL HWND hwndFocus = NULL;            // Focus window
_LOCAL HWND hwndActive = NULL;           // Active window
_LOCAL HWND hwndParent;                  // Current parent interrogated.
_LOCAL HWND hwndPrvParent;               // This was the previous parent.

_LOCAL int iCaptionLen;                  // The longest context caption length.
_LOCAL int iDebugCapLen;
_LOCAL int iGroupLevel;                  // The context group number.

_LOCAL FARPROC lpprocContext = NULL;

_LOCAL char szCaptionBuf[2 * MAX_SYMBOL_LENGTH + 50];    // Caption buffer.

_LOCAL LPLANG pLangCur = NULL;

/*-----
|
| These are switches
|
*/
_LOCAL BOOL bChildSysMenu;    // Child sys commands used ?
_LOCAL HWND hwndMenuSysPop;   // Is the sys menu popped up ?
_LOCAL BOOL bMenuBarExist;
_LOCAL BOOL bMenuPopExist;    // Is there a popup menu active.
_LOCAL int iScrollMask;       // Is scroll present mask.

/*-----
|
| These are predefined classes.
|
*/
_LOCAL PSTR szPredefClass[] =
{
    "Static",
    "Button",
    "ListBox",
    "ComboBox",
    "Edit",
    "ScrollBar",
    "PMGroup",           // Program manager groups.
    "MDIClient",
};

/*-----
|
| FUNCTION _LOCAL void ContextListInit(void)

```

DESCRIPTION Clear the previous context list.

PARAMETERS None.

RETURN None.

```

/*
LOCAL void ContextListInit(void)
{
    /* Delete old context list
    */
    while (pciFirst != NULL)
    {
        pciLast = pciFirst->pciNext;
        if (pciFirst->conType == CON_LAUNCH)
        {
            /* We allocate these string
            */
            StringNearDestroy(pciFirst->u.PMItem.szTitle);
            StringNearDestroy(pciFirst->u.PMItem.szFile);
        }
        Nfree(pciFirst);
        pciFirst = pciLast;
    }

    /* Reset the checking environment.
    */
    iCheckSum = 0;

    /* Leave 0 for the lang overrides.
    */
    iGroupLevel = 1;

    /* A pop up menu is on top.
    */
    hwndMenuSysPop = NULL;

    /* The menu bar has been read ?
    */
    bMenuBarExist = FALSE;

    /* Child sys commands used ?
    */
    bChildSysMenu = FALSE;

    /* No scroll commands yet
    */
    iScrollMask = 0;
}

```

```

/*
FUNCTION  _LOCAL BOOL ContextAdd(hwnd, conType)

```

DESCRIPTION Add an item of context info to the list.

Filling in the union feilds is up to the caller.

PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
int conType -

RETURN TRUE if success

```
*/
LOCAL BOOL ContextAdd(HWND hwnd, int conType)
{
    CONTEXTITEM * pci;
    int c;

    if (pciLast != NULL)
    {
        /* Checksum the previous.
        */
        for (c = 0; c < sizeof(CONTEXTITEM); c++)
        {
            iChecksum += ((PSTR) pciLast)[c];
        }
    }

    /* Must have a window ?
    */
    if (hwnd == NULL)
        return(FALSE);

    /* Allocate struct
    */
    pci = (CONTEXTITEM*) Nmalloc(sizeof(CONTEXTITEM));
    if (pci == NULL)
        return(FALSE);

    /* Set basic vars
    */
    pci->conType = conType;
    pci->iLevel = iGroupLevel;
    pci->hwnd = hwnd;

    /* Insert it after the pciLast.
    */
    if (pciFirst == NULL || pciLast == NULL)
    {
        /* At the start.
        */
        pci->pciNext = pciFirst;

        /* save top.
        */
        pciFirst = pci;
    }
    else
    {
        /* Insert after pciLast.
        */
    }
}
```

```

pci->pciNext = pciLast->pciNext;

/* Add to end.
*/
pciLast->pciNext = pci;
}

/* The current pointer.
*/
pciLast = pci;

/* Return true so we continue enumerating.
*/
return(TRUE);
}

/*-----
FUNCTION  _LOCAL BOOL HasKey(hMenu, iPos)

DESCRIPTION Check if the given menu has accelerator key.
                We check only \t, \a, or \b presents in the string

PARAMETERS  HWND hMenu - Specifies handle to the given menu.
            int iPos - specifies position in the menu

RETURN

*/
_LOCAL BOOL HasKey(HMENU hMenu, int iPos)
{
    int i;

    if(! GetMenuString(hMenu, iPos, szCaptionBuf, sizeof(szCaptionBuf) - 1,
MF_BYPOSITION))
    {
        /* No text at all
        */
        return(FALSE);
    }

    for (i = 0; i < strlen(szCaptionBuf) - 1; i++)
    {
        if (szCaptionBuf[i] == '\t' || // For Windows Apps
            szCaptionBuf[i] == '\a' ||
            szCaptionBuf[i] == '\b') // For Microsoft Apps
        {
            /* Has TAB or ...
            */
            return(TRUE);
        }
    }
    return(FALSE);
}
}

```



```

    }
}

/*-----
FUNCTION  _LOCAL BOOL ContextAddMenu(HWND hwnd, HMENU hMenu)
DESCRIPTION Add the menu options to the context list.
PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
              HWND hMenu - Specifies handle to the given menu.
RETURN     None.
*/
_LOCAL BOOL ContextAddMenu(HWND hwnd, HMENU hMenu)
{
    int i;
    int items;
    WORD State;
    int numseparators;

    if (hMenu == NULL)
    {
        /* No menu
        */
        return(FALSE);
    }

    /* For all items
    */
    items = GetMenuItemCount(hMenu);
    numseparators = 0;
    for (i = 0; i < items; i++)
    {
        State = GetMenuState(hMenu, i, MF_BYPOSITION);
        if (State == -1)
            break;
        if (!ContextAdd(hwnd, (State & MF_POPUP) ? CON_MENUPOPUP :
CON_MENU))
            return(FALSE);

        /* Popups return different values
        */
        if (!(State & MF_POPUP))
        {
            /* Skip separator
            */
            if (State & MF_SEPARATOR)
                numseparators++;
        }

        if (pciLast->conType == CON_MENUPOPUP)
        {
            /* Store the entry number.

```

FOR "5248260"

```

        */
        pciLast->u.MenuPop.iEntry = i;
        pciLast->u.MenuPop.iKeyPos = i - numseparators;
        pciLast->u.MenuPop.hMenu = hMenu;
    }
    else
    {
        /* Store ID.
        */
        pciLast->u.Menu.id = GetMenuItemID(hMenu, i);
        pciLast->u.Menu.hMenu = hMenu;
    }
}
return(TRUE);
}

```

```

/*-----
FUNCTION    void ContextNewLang(pLangEdit)
DESCRIPTION Change macro language.
PARAMETERS LPLANG pLangEdit - Specifies pointer to the new language.
RETURN     None.
*/
void ContextNewLang(LPLANG pLangEdit)
{
    char szFile[MAXFILENAME + 1];

    /* Destroy old language if present
    */
    LangChainDestroy(pLangCur);

    if (pLangEdit == NULL)
    {
        /* Try to open users language
        */
        Ini GetUserFile(szFile);
        lstrcat(szFile, ".LNG");
        pLangCur = LangLoad(szFile);
    }
    else
    {
        /* Try to copy from editor
        */
        pLangCur = LangChainMake(pLangEdit);
    }

    if (pLangCur == NULL)
    {
        /* Try to open default language
        */
        IniGetLangFile(szFile);
    }
}

```

00725-04104
T04T00-522E2460

```

    pLangCur = LangLoad(szFile);
}

```

```

}

```

```

/*-----

```

```

FUNCTION _LOCAL LPLANG GetActiveLang()

```

```

DESCRIPTION A new task has been loaded so load new language
            or the default language.

```

```

PARAMETERS None.

```

```

RETURN     Pointer to the app specific language.

```

```

*/

```

```

_LOCAL LPLANG GetActiveLang()

```

```

{

```

```

    static HWND  hwndPrevActive = NULL;

```

```

    static LPLANG pActiveLang = NULL;

```

```

    HANDLE hTask;

```

```

    TASKENTRY te;

```

```

    char szFile[MAXFILENAME + 1];

```

```

    /* Active window changed

```

```

    */

```

```

    if (hwndPrevActive != hwndActive)

```

```

    {

```

```

        /* Save currently active window for the next call

```

```

        */

```

```

        hwndPrevActive = hwndActive;

```

```

        /* Get task handle

```

```

        */

```

```

        hTask = GetWindowTask(hwndActive);

```

```

        if (hTask == NULL)

```

```

        {

```

```

            /* No task ?!

```

```

            */

```

```

            pActiveLang = NULL;

```

```

        }

```

```

        else

```

```

        {

```

```

            /* Get module name

```

```

            */

```

```

            te.dwSize = (DWORD) sizeof(te);

```

```

            TaskFindHandle((TASKENTRY FAR *) &te, hTask);

```

```

            GetModuleFileName(te.hModule, (LPSTR)szFile, sizeof(szFile) - 1);

```

```

            /* Try to find language

```

```

            */

```

```

            for (pActiveLang = pLangCur->pNext; pActiveLang != NULL;

```

```

                pActiveLang = pActiveLang->pNext)

```

TOP SECRET

```

        {
            if (! lstrcmpi(szFile, pActiveLang->szFile))
            {
                /* Here it is
                */
                break;
            }
        }
    }

    /* Return pointer to the language or NULL
    */
    return(pActiveLang);
}

```

```

/*-----
FUNCTION  _LOCAL void AddLang(pLang, hwnd, szClass, szWndText, bMenuPopExist )

DESCRIPTION Add macro command from the language

PARAMETERS LPLANG pLang - Specifies pointer to the language.
            HWND hwnd - Specifies handle to the window we are looking at.
            PSTR szClass - Specifies pointer to the class name string.
            PSTR szWndText - Specifies pointer to the windows title.
            BOOL bMenuPopExist - TRUE if popup menu on the screen.

RETURN    None.
*/
_LOCAL void AddLang(LPLANG pLang, HWND hwnd, PSTR szClass, PSTR szWndText, BOOL
bMenuPopExist )
{
    LPGROUP pGroup;
    LPMACRO pMacro;
    HWND hwndMacro;

    if (pLang == NULL)
        /* No language selected
        */
        return;

    /* Try to find proper group
    */
    for (pGroup = pLang->pGroup; pGroup != NULL; pGroup = pGroup->pNext)
    {
        if (
            /* Default group
            */
            (pGroup->szClass == NULL && szClass == NULL)
            /* Class group
            */
            ||(( pGroup->szClass != NULL && szClass != NULL && !
lstrcmp(pGroup->szClass, szClass)

```

104120-3226260

pci->pciNext)

CON_WIND)

and child ID

>hwnd, szBuf, sizeof(szBuf)-1);

GetWindowWord(pci->hwnd, GWW_ID) &&

pMacro->szWndClass))

found it

pci->hwnd;

menu on the screen

for (pci = pciFirst; pci != NULL; pci =

{

if (pci->conType ==

{

/* Compare class name

*/

GetClassName(pci-

if (pMacro->itemid ==

! strcmp(szBuf,

{

/* we have

*/

hwndMacro =

break;

}

}

}

if (hwndMacro == NULL)

{

/* No window

*/

break;

}

}

}

default:

if (bMenuPopExist)

/* Can not do anything while popup

*/

break;

if (! ContextAdd(hwndMacro, CON_MACRO))

/* Not enough memory

*/

return;

/* Add it

*/

pciLast->u.pMacro = pMacro;

}

}

}

}

}


```

/*-----
FUNCTION  _LOCAL void AddLngCommands(hwnd, szClass, szWndText, bMenuPopExist )

DESCRIPTION Add macro command.

PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
           PSTR szClass - Specifies pointer to the class name string.
           PSTR szWndText - Specifies pointer to the windows title.
           BOOL bMenuPopExist - TRUE if popup menu on the screen.

RETURN   None.
*/

```

```

_LOCAL void AddLngCommands(HWND hwnd, PSTR szClass, PSTR szWndText, BOOL
bMenuPopExist )
{
    if (pLangCur == NULL)
    {
        /* No language at all
        */
        return;
    }

    /* Application specific language
    */
    AddLang(GetActiveLang(), hwnd, szClass, szWndText, bMenuPopExist);

    /* Global language
    */
    AddLang(pLangCur, hwnd, szClass, szWndText, bMenuPopExist);
}

```

```

/*-----
FUNCTION  _LOCAL void AddScrollBarCommands(hwnd, ScrollMask, iCheckMask)

DESCRIPTION Create scroll bar command.

PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
           int ScrollMask - Specifies scroll mask.
           int iCheckMask - Specifies check mask.

RETURN   None.
*/

```

```

_LOCAL void AddScrollBarCommands(HWND hwnd, int ScrollMask, int iCheckMask)
{
    /* Scroll command with this name shouldn't be in the list twice
    */
    if (! (iScrollMask & iCheckMask))
    {
        /* This is first one

```

U:\P00000000\00000000

```
*/
iScrollMask |= iCheckMask;

if (! ContextAdd(hwnd, CON_SCROLL))
    /* Not enough memory
    */
    return;
pciLast->u.ScrCom = SB_LINEUP | ScrollMask;

if (! ContextAdd(hwnd, CON_SCROLL))
    /* Not enough memory
    */
    return;
pciLast->u.ScrCom = SB_LINEDOWN | ScrollMask;

if (! ContextAdd(hwnd, CON_SCROLL))
    /* Not enough memory
    */
    return;
pciLast->u.ScrCom = SB_PAGEUP | ScrollMask;

if (! ContextAdd(hwnd, CON_SCROLL))
    /* Not enough memory
    */
    return;
pciLast->u.ScrCom = SB_PAGEDOWN | ScrollMask;

    }

}

/*-----
FUNCTION  _LOCAL void ContextAddScrollBars(hwnd, Style, cwc)
DESCRIPTION Add scroll bar commands.

PARAMETERS  HWND hwnd - Specifies handle to the window we are looking at.
            LONG Style - Specifies windows style
            int cwc - Specifies window type.

RETURN      None.
*/
_LOCAL void ContextAddScrollBars(HWND hwnd, LONG Style, int cwc)
{
    switch (cwc)
    {
        case CWC_MDICLIENT:
            if (Style & WS_VSCROLL)
            {
                AddScrollBarCommands(hwnd, SCRLS_MDI, SCRLM_VMDI);
            }
            if (Style & WS_HSCROLL)
            {

```

```

        AddScrollBarCommands(hwnd, SCRLS_MDI | SCRLS_HORZ,
SCRLM_HMDI);
    }
    break;

    case CWC_SCROLLBAR :
        if (Style & SBS_VERT)
        {
            AddScrollBarCommands(hwnd, SCRLS_WIN, SCRLM_VERT);
        }
        else
        {
            AddScrollBarCommands(hwnd, SCRLS_WIN | SCRLS_HORZ,
SCRLM_HORZ);
        }
        break;

    default:
        if (Style & WS_VSCROLL)
        {
            AddScrollBarCommands(hwnd, 0, SCRLM_VERT);
        }
        if (Style & WS_HSCROLL)
        {
            AddScrollBarCommands(hwnd, SCRLS_HORZ,
SCRLM_HORZ);
        }
    }
}

```

```

/*-----
FUNCTION  _LOCAL void ContextAddWindSysCom(hwnd, Style)
DESCRIPTION Add system type commands for the window.
PARAMETERS HWND hwnd - Specifies handle to the given window.
            LONG Style - Specifies windows style
RETURN    None.

NOTE      Maximized MDI children are strange.
          The sys menu/restore is in the main menu of parent.
          They will not register normal WS_SYSMENU and restore boxes.
          Microsoft Excel violates even these rules !
          It will not set the WS_MAXIMIZE bit !
*/
_LOCAL void ContextAddWindSysCom(HWND hwnd, LONG Style)
{
    if (! (Style & WS_CHILD) || ! (Style & WS_MAXIMIZE))
    {
        /* Does the window have system command menu ?
        */
        if (! (Style & WS_SYSMENU))
            return;
    }
}

```

C:\WINDOWS\SYSTEM32\cmd.exe

TOP SECRET 9226260

```
}
else
{
    /* Can we get one ?
    */
    if (GetSystemMenu(hwnd, FALSE) == NULL)
        return;
}

/* Already got sysmenu type stuff ?
*/
if (bChildSysMenu && (Style & WS_CHILD))
    return;
bChildSysMenu = TRUE;

/* Check to see if sys menu is already popped up.
*/
if (hwndMenuSysPop == hwnd)
    /* Already popped.
    */
    return;

/* Option to pull down the sys menu.
*/
if (! ContextAdd(hwnd, CON_SYSCOM))
    return;
/* The menu itself.
*/
pciLast->u.SysCom = SC_KEYMENU;

/* If the window is iconic then the others are not really available.
** Although they will say they are.
*/
if (Style & WS_ICONIC)
    return;

/* Option to close the window or app
** This is equiv. to double click on sys menu box.
*/
if (! ContextAdd(hwnd, CON_SYSCOM))
    return;
pciLast->u.SysCom = SC_CLOSE;

/* Get the min/max controls seperatly for now.
*/
if (Style & WS_MINIMIZEBOX)
{
    if (! ContextAdd(hwnd, CON_SYSCOM))
        return;
    pciLast->u.SysCom = SC_MINIMIZE ;
}

/* If the window is maximized then we need a restore box.
*/
if (Style & WS_MAXIMIZEBOX)
{
```

```

        if (! ContextAdd(hwnd, CON_SYSCOM))
            return;
        pciLast->u.SysCom = (Style & WS_MAXIMIZE) ? SC_RESTORE :
SC_MAXIMIZE ;
    }
}

```

```

/*-----
FUNCTION  _LOCAL void ContextAddPMGroup(hwnd, Style)
DESCRIPTION Add content of Program Manager Group
PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
            LONG Style - Specifies windows style
RETURN    None.
*/

```

```

_LOCAL void ContextAddPMGroup(HWND hwnd, LONG Style)
{
    SHELLITEM si;
    BOOL  bRet;

    if (Style & WS_ICONIC)
    {
        /* We dont look inside iconic window, user cannot either
        */
        return ;
    }
    /* Window text is a group name
    */
    GetWindowText(hwnd, szCaptionBuf, sizeof(szCaptionBuf) - 1);

    /* Enumerate PM items inside the group
    */
    bRet = ShellGetFirstItem(&VCTalk, szCaptionBuf, &si);
    while (bRet)
    {
        /* We need command string to execute
        */
        if (si.szFile)
        {
            if (! ContextAdd(hwnd, CON_LAUNCH))
                /* not enough memory
                */
                return;

            /* Title is the name, file is the command string
            */
            pciLast->u.PMItem.szTitle = StringNearMake(si.szTitle);
            pciLast->u.PMItem.szFile = StringNearMake(si.szFile);
        }

        /* Next one ?
        */
    }
}

```

0070373E-0340
F04F03E26260

```

        bRet = ShellGetNextItem(&VCTalk, &si);
    }
}

```

```

/*-----
FUNCTION  _LOCAL BOOL ContextAddWind(hwnd, checktype)

DESCRIPTION Check the window for useful context info.

PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
            int checktype - what type are we looking at. CW_*

RETURN    TRUE if success.

NOTE      Windows have the attributes of:
          window handle
          window caption text, GetWindowText()
          parent handle,   GetParent()
          rectangle.      GetWindowRect() GetClientRect()
          child id number. GetDlgCtrlID()
          Enabled or disabled. IsWindowEnabled(hwnd)
          Active or Inactive. GetActiveWindow() ?
          Have focus ?      GetFocus()

          Window Class attributes. WNDCLASS. GetClassInfo
          style bit mask.
          class name. GetClassName ?
          module handle, Module name GetModuleFileName
          ? cursor
          ? icon
          ? Menu bar resource name.

          In the future we want to add special controls for known classes.
          SCROLLBAR = bars may not be sub windows but part of the non client !
          BUTTON = none needed but press.
          STATIC = not needed but may label another control.
          COMBOBOX = may have scrollbars, pull down, options inside ?
          EDIT = scroll bars, new or dictated text ?
          LISTBOX

          We start from the bottom and work up. but previous parents are special.
          Don't duplicate the parent of current focus.

*/
_LOCAL BOOL ContextAddWind(HWND hwnd, int checktype)
{

```

```

    LONG Style;
    int cwc;
    int conType = CON_WIND; /* default object type. */
    char szClass[MAXSTRING + 1];
    char szWndText[MAXSTRING + 1];
    PREF_FLAGS prefFlags = UserGetFlags();

```

1044 3226260

00703726-0440
T04T020-9226260

```
}

/* We must be focus or a parent of the focus to get menus and parts.
*/
if ((checktype & CW_HASFOCUS) && (conType != CON_ICON))
{
    /* Does the window have a menu bar ?
    */
    if (
        /* Not a child window.
        */
        ! (Style & WS_CHILD) &&
        /* Already have a menu, ONLY WANT ONE.
        */
        ! bMenuBarExist)
    {
        /* Get a menu bar if there is one.
        */
        if ((prefFlags & PREF_Menu) && ContextAddMenu(hwnd,
GetMenu(hwnd)))
        {
            bMenuBarExist = TRUE;
        }
    }

    /* FOR NOW, if a popup menu is active the window is not ???
    */
    if (! bMenuPopExist)
    {
        /* Add accelerators.
        */
        if (bMenuBarExist && (prefFlags & PREF_Accel))
        {
            ContextAddAccel(hwnd, GetMenu(hwnd));
        }

        /* Add contents of PMGroup
        */
        if (checktype == CW_HASFOCUS && cwc == CWC_PMGROUP &&
(prefFlags & PREF_WndChild))
        {
            ContextAddPMGroup(hwnd, Style);
        }

        /* Get system type commands.
        */
        if (prefFlags & PREF_SysCom)
        {
            ContextAddWindSysCom(hwnd, Style);
        }
    }
}
```



```

/* GetMenu() is undefined for WS_CHILD types.
*/
if (! (Style & WS_CHILD))
{
    if (hMenu == GetMenu(hwnd))
        bMenuBarExist = TRUE;
}

/* Add menu without accelerators
*/
if (UserGetFlags() & PREF_Menu)
{
    if (ContextAddMenu(hwnd, hMenu))
    {
        iGroupLevel++;
    }
}

/* Is it a system menu
*/
if (hMenu == GetSystemMenu(hwnd, FALSE))
{
    hwndMenuSysPop = hwnd;
}
}

/*-----
|
| FUNCTION  BOOL CALLBACK ContextEnumProc(hwnd, IParam)
|
| DESCRIPTION Callback function that receives window handles as
|              a result of a call to the EnumWindows function.
|
| PARAMETERS HWND hwnd - Specifies handle of the target window.
|              LONG IParam - What do we do with the data once we have it ?
|
| RETURN    Return nonzero to continue enumeration.
|
*/
BOOL FAR PASCAL ContextEnumProc(HWND hwnd, LONG IParam)
{
    return (ContextAddWind(hwnd, (int) IParam));
}

/*-----
|
| FUNCTION  _LOCAL char StringGetSysChar(String)
|
| DESCRIPTION Get underlined symbol from the menu item.
|
| PARAMETERS PSTR String - Specifies menu string.
|
| RETURN    Underlined symdol.
|
*/

```

```

_LOCAL char StringGetSysChar(PSTR String)
{
    while (*String)
    {
        if (*(String++) == '&')
        {
            /* We have found &
            */
            break;
        }
    }
    /* Return address of the next one
    */
    return(*String);
}

```

```

/*-----
| FUNCTION  _LOCAL int ContextPakWind(hwnd)
| DESCRIPTION Pak a string description for the window type object.
|             User pciLast to identify the object.
| PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
| RETURN    Length of the caption text.
|
*/

```

```

_LOCAL int ContextPakWind(HWND hwnd)
{

```

```

    int len;

```

```

    /* If window not active then ignore it.
    */

```

```

    if (

```

```

        (! IsWindowEnabled(hwnd)

```

```

        || ! IsWindowVisible(hwnd)))

```

```

        /* Not really working ??? */

```

```

        return(0);

```

```

    /* What is its caption text ?
    */

```

```

    len = GetWindowText(hwnd, szCaptionBuf, sizeof(szCaptionBuf) - 1);

```

```

    /*

```

```

    /* What is its class.
    */

```

```

    switch (pciLast->u.Window.cwc)

```

```

    {

```

```

        case CWC_EDIT:

```

```

        case CWC_COMBOBOX:

```

```

        case CWC_LISTBOX:

```

```

        case CWC_SCROLLBAR:

```

```

            /* Edit/Comb/List captions are the current text inside them ?
            */

```

```

            len = 0;

```

```

            break;

```



```

"%s %s",
(LPSTR)Str,
(LPSTR)UserGetDefWord((GetWindowLong(hwnd,GWL
_STYLE) & WS_CHILD) ? IDW_CHILD : IDW_POPUP));
    }

    return(len);
}

```

```

/*-----
FUNCTION  _LOCAL int ContextPakScroll(iScrCom)
DESCRIPTION Create scroll command string.
PARAMETERS int iScrCom - Specifies scroll command.
RETURN     Length of the caption text.
*/
_LOCAL int ContextPakScroll(int iScrCom)
{

```

```

    int len;
    int idWord;

    /* First try all type of horizontall scroll
    */
    if (iScrCom & SCRLS_HORZ)
    {
        switch (pciLast->u.ScrCom & SCRLS_ACT)
        {
            case SB_LINEUP:
                /* line left
                */
                idWord = IDW_LINELEFT;
                break;
            case SB_LINEDOWN:
                /* line right
                */
                idWord = IDW_LINERIGHT;
                break;
            case SB_PAGEUP:
                /* page left
                */
                idWord = IDW_PAGELEFT;
                break;
            case SB_PAGEDOWN:
                /* page right
                */
                idWord = IDW_PAGERIGHT;
                break;
        }
    }

    /* Now all type of vertical scroll

```

TOP SECRET


```

        else {
            len = ContextPakMenu(pciLast->u.Menu.hMenu, pciLast-
>u.Menu.id, MF_BYCOMMAND);
        }
        break;

    case CON_MENUPOPUP:
        /* Read an item from the menu bar.
        */
        len = ContextPakMenu(pciLast->u.MenuPop.hMenu, pciLast-
>u.MenuPop.iEntry, MF_BYPOSITION);
        break;

    case CON_ACCEL:
        /* Accelerator has the same text as a menu item (it available thought)
        */
        len = GetMenuString(pciLast->u.Acc.hMenu, pciLast->u.Acc.id,
szCaptionBuf,
                            sizeof(szCaptionBuf) - 1, MF_BYCOMMAND);
        break;

    case CON_LAUNCH :
        /* PM item title
        */
        lstrcpy(szCaptionBuf, pciLast->u.PMItem.szTitle);
        len = strlen(szCaptionBuf);
        break;

    case CON_MACRO:
        /* Macro name
        */
        lstrcpy(szCaptionBuf, (pciLast->u.pMacro)->szName);
        len = strlen(szCaptionBuf);
        break;

    default: return(0);
}

/* Chop out the ampersands (&) and tabs.
*/
if (len)
    len = StringClip(szCaptionBuf);
else
    *szCaptionBuf = '\0';

if (len > iCaptionLen)
    iCaptionLen = len;

#ifdef DEBUG_DLG
/* Pack debug info
*/
if (DebugFlag & DEBUG_ContFull)
{
    len = ContextPakDebug();
    if (len > iCaptionLen) iCaptionLen = len;
}

```

007022-0340

#endif

```
/* Return length of the string
*/
return(len);
```

}

```
/*-----
FUNCTION  BOOL ContextCheck(bPrefChange)

DESCRIPTION Hook the context window to the status window.

PARAMETERS  BOOL bPrefChange - Rebuild list anyway

RETURN      TRUE = A change in the context ?

NOTE        This is called every so often to check for context changes.
              Watch for the change in focus thru the hook routines ?
              Menus don't change the focus ! we must watch messages for them !
              When we select an icon the focus = null the active window is icon.
```

```
*/
BOOL ContextCheck(BOOL bPrefChange)
{
    int    checktype;
    int    changetype;
    unsigned PrevCheckSum;

    changetype = HookGet_Change();

    /* Does anything change ?
    */
    if (changetype == HCHANGE_NONE && ! bPrefChange)
        return(FALSE);

    /* Set up to enumerate the windows.
    */
    if (lpprocContext == NULL)
    {
        lpprocContext = MakeProcInstance(ContextEnumProc, VChInst);
    }

    /* First we check context save options (when old focus valid).
    */
    if (GetWindowTask(GetActiveWindow()) == GetCurrentTask())
    {
        if (IsWindow(hwndFocus) && (! IsIconic(hwndActive) || hwndActive ==
hwndFocus))
        {
            /* Context still good for now, but we need to check preferences
            */

```



```

    {
        if (! IsWindowEnabled(hwndParent)) /* The previous was top. */
            break;

        if (! IsIconic(hwndParent))
        {
            EnumChildWindows(hwndParent, lpprocContext, checktype);
            iGroupLevel ++;
        }

        /*
        ** Store the parent level. (May not be a real option.)
        */
        ContextAddWind(hwndParent, CW_HASFOCUS | checktype);
        hwndPrvParent = hwndParent; /* Don't duplicate in siblings. */
        iGroupLevel ++;
        checktype = CW_PARENTLEVEL;

        /*
        ** Break after Active window
        */
        if (hwndParent == hwndActive)
        {
            break;
        }

        /*
        ** Does it have a parent ?
        */
        hwndParent = GetParent(hwndParent);
    }

}

/*
** Get other applications. except if someone above is system modal.
** WS_OVERLAPPED and WS_POPUP type windows.
*/
EnumWindows(lpprocContext, 0);

ContextAdd(NULL, 0); /* Checksum the last. */

return(PrevCheckSum != iCheckSum || changetype > HCHANGE_POSSIBLE);
}

```

```

| FUNCTION void ContextListAdd(void)
|
| DESCRIPTION Build a list of siblings and children.
|
| PARAMETERS None.
|
| RETURN None.
|

```

```

*/
void ContextListAdd(void)
{
    int len;
    int iEntry = 0;

    ContextCheck(FALSE);          /* One final check before packing. */

    iCaptionLen = 13;             /* Minimum size. */

#ifdef DEBUG_DLG
    iDebugCapLen = 0;
#endif

    for (pciLast = pciFirst; pciLast != NULL; pciLast = pciLast->pciNext, iEntry++)
    {

        len = ContextPak();
        if (! len) continue;

        /* Send a message adding the window caption to the list
        ** in the dialog.
        */
        if (! PhraseListAdd(szCaptionBuf, iEntry)) break;
    }

#ifdef DEBUG_DLG
    /* Set the tabs and columns.
    */
    if (DebugFlag & DEBUG_ContFull)
    {

        ContextTabs[0] = (iCaptionLen + 4) * 10;
        ContextTabs[1] = (iCaptionLen + 12) * 10;
        ContextTabs[2] = iCaptionLen + 16 + iDebugCapLen;

    }
#endif
}

/*-----
FUNCTION    void ContextListSelect(iEntry)

DESCRIPTION The user selected a word from the list.
             Take some default MACRO action based on the context type

PARAMETERS int iEntry - Specifies number of list item;

RETURN     None.
*/
void ContextListSelect(int iEntry)
{
    HWND hwnd;
    MACRO macro;

```

TOP SECRET

```

if (iEntry < 0) return;

/*
** Find the window in the list.
*/
for (pciLast = pciFirst; iEntry; iEntry --)
{
    if (pciLast == NULL)
        return; /* THIS SHOULD NEVER HAPPEN */
    pciLast = pciLast->pciNext;
}
hwnd = pciLast->hwnd;

/* We keep focus and it valid.
*/
if (GetWindowTask(GetActiveWindow()) == GetCurrentTask())
{
    SetFocus(hwndFocus);
}

/* Default macros are to be executed on hwnd.
*/
macro.szWndClass = NULL;
macro.szDesc     = NULL;
macro.pNext      = NULL;

switch (pciLast->conType) {

    case CON_SYSCOM:
        /* A system command from the system command menu to the window.
        ** PostMessage(hwnd, WM_SYSCOMMAND, iEntry, NULL);
        */
        macro.cmdType      = CMD_SYSTEM;
        macro.Cmd.System.wCmd = pciLast->u.SysCom;
        break;

    case CON_SCROLL:
        /* PostMessage
        */
        macro.cmdType      = CMD_MESSAGE;
        macro.Cmd.Msg.wMsg = (pciLast->u.ScrCom & SCRLS_HORZ) ?
WM_HSCROLL : WM_VSCROLL;
        macro.Cmd.Msg.wParam = pciLast->u.ScrCom & SCRLS_ACT;

        if (pciLast->u.ScrCom & SCRLS_WIN)
        {
            macro.Cmd.Msg.lParam = MAKELONG(0, hwnd);
            hwnd = GetParent(hwnd);
        }
        else
        {
            macro.Cmd.Msg.lParam = 0L;
        }
        break;

```

```

case CON_ICON:
    /* Restore the iconic window.
    ** NOTE:
    ** Iconic windows don't get focus. they just activate.
    ** OpenIcon(hwnd);
    */
    macro.cmdType = CMD_SYSTEM;
    macro.Cmd.System.wCmd = SC_RESTORE;
    break;

case CON_WIND:
    if ((pciLast->u.Window.cwc == CWC_STATIC) || (pciLast-
>u.Window.cwc == CWC_GROUPBOX))
    {
        GetWindowText(hwnd, szCaptionBuf, sizeof(szCaptionBuf) - 1);
        macro.cmdType = CMD_KEY;
        macro.Cmd.Key.cKey = (char)
VkKeyScan(StringGetSysChar(szCaptionBuf));
        macro.Cmd.Key.AltPressed = (BYTE) 1;
        macro.Cmd.Key.ShiftPressed = (BYTE) 0;
        macro.Cmd.Key.CtrlPressed = (BYTE) 0;
    }
    else
    {
        /* Choose the window as the current window. For top level
        windows this
        ** will result in their being activated. For items in dialog boxes
        ** this will result in their being selected.
        */
        macro.cmdType = CMD_SELECT;
    }
    break;

case CON_MENUPOPUP:
    /* An item on the windows menu bar.
    ** Pull down the popup menu.
    */
    macro.cmdType = CMD_MENUPOPUP;
    macro.Cmd.MenuPopup.iKeyPos = pciLast->u.MenuPop.iKeyPos;

    if (GetMenu(hwnd) == pciLast->u.MenuPop.hMenu)
        macro.Cmd.MenuPopup.wLevel = 0;
    else
        macro.Cmd.MenuPopup.wLevel = 1;
    break;

case CON_MENU:
    /* A menu item in the active menu.
    ** Execute the menu item.
    ** PostMessage(hwnd, WM_COMMAND, iEntry, NULL);
    */

```

```

if (hwndMenuSysPop)
{
    /* Menu item chosen from system menu.
    */
    macro.cmdType = CMD_SYSTEM;
    macro.Cmd.System.wCmd = pciLast->u.Menu.id;
}
else
{
    /* Menu item chosen from the menu bar.
    */
    macro.cmdType = CMD_MENU;
    macro.Cmd.Menu.id = pciLast->u.Menu.id;
}
break;

case CON_ACCEL:
    /* Accelerator key
    */
    macro.cmdType = CMD_MENU;
    macro.Cmd.Menu.id = pciLast->u.Acc.id;
    break;

case CON_LAUNCH:
    /* Just execute
    */
    macro.cmdType = CMD_LAUNCH;
    macro.szDesc = pciLast->u.PMItem.szFile;
    break;

case CON_MACRO:
    macro.cmdType = pciLast->u.pMacro->cmdType;
    macro.Cmd = pciLast->u.pMacro->Cmd;
    macro.itemid = pciLast->u.pMacro->itemid;
    macro.szDesc = pciLast->u.pMacro->szDesc;
    break;

default :
    return;
}

VCM_Execute(&macro, hwnd);

```

```

}

```

0070336-03401


```

/*
** File: HOOK.C
**
** Module for Hooking Window's queue and tracking relevant messages.
**
** Interface functions: HookGet_Change
**                      HookGet_Menu
**                      HookGet_MenuAtLevel
**                      HookGet_MenuLevel
**                      HookGet_MenuWnd
**                      HookInstall
**                      HookJournalBusy
**                      HookFreeJournal
**                      Record
**
** Exported functions: HookMain
**                      HookGetMsgProc
**                      HookSndMsgProc
**                      PlayProc
**                      RecProc
**
** Private functions: HookMenuClear
**                      HookMessage
**                      PlayNotify
**                      RecNotify
**
*****
*****/

#include <windows.h>
#include "vtools.h"

typedef struct
{
    // Another message type
    DWORD lParam;           /* This was backwards before ? */
    WORD wParam;
    WORD wMsg;
    HWND hWnd;
} CALLWNDPROC;           /* NOTE: Parameters are oposite of LPMMSG ? */

typedef CALLWNDPROC FAR *LPCALLWNDPROC;

/*-----
|
| Module local variables.
|
*/

HANDLE hInst;           // Instance Handle given in LibMain()
HHOOK hGetMsgHook;      // Handle to the getmessage hook
HHOOK hSndMsgHook;      // Handle to the callwndproc hook
HHOOK hJournalHook;     // Current journal record/playback hook function

/*-----
|
| --- Variables for Playback ---
|

```

```

*/
static LPRECORD lpJmlList; // Handle to the list of journal events
static BOOL bJournalBusy; // Is the DLL busy recording or playing back?
static DWORD dwInitPlaybackTime; // Initial time of Playback() call
static short sPlaybackSpeed; // Speed given to Playback() (0 or -1)
static DWORD dwPrevMsgTime; // Time of previously played back event

```

```

static HWND hWndNotify;
static UINT wMsgNotify;
static UINT wStopKey;
static UINT wMouRec;

```

```

/*-----
|
| --- Context manager tracking. ---
|
*/

```

```

static int Hook_Change; // context change type. */
static HWND Hook_MenuhWnd; // The window owning the menu. */
static int Hook_MenuLevel; // The menu stack level. -1=none */
static HMENU Hook_MenuSelect; // Selected item from the current level. */

```

```

static enum
{

```

```

    /*
    ** If we are tracking a multi message operation.
    */
    HT_NONE, // Watch for nothing. */
    HT_ACCEL, // Watch for an accelerator key press. */
} Hook_Track;

```

```

#define MENUSTACKQTY 6 // How many sub levels to store. */

```

```

static HMENU Hook_MenuStack[MENUSTACKQTY]; // currently active menu. */

```

```

/*-----

```

```

FUNCTION int CALLBACK HookMain(hinst, wDataSeg, wHeapSize, lpszCmdLine)

```

```

DESCRIPTION Part of the LibMain that belongs to the hook system.

```

```

PARAMETERS HINSTANCE hinst - Identifies the instance of the DLL.

```

```

    WORD wDataSeg - Specifies the value of the data
                    segment (DS) register.

```

```

    WORD wHeapSize - Specifies the size of the heap defined
                    in the module-definition file.

```

```

    LPSTR lpszCmdLine - Points to a null-terminated string
                       specifying command-line information.

```

```

RETURN 1 if it is successful. Otherwise, it should return 0.

```

```

*/
int CALLBACK HookMain(HINSTANCE hinst, WORD wDataSeg, WORD wHeapSize, LPSTR
lpszCmdLine)
{

```

T04120"5243260

```

hInst = hinst;
bJournalBusy = FALSE;
hGetMsgHook = NULL;
hSndMsgHook = NULL;

Hook_Change = HCHANGE_NONE;
Hook_MenuLevel = -1;
Hook_Track = HT_NONE;

return (TRUE);
}

```

```

/*-----
FUNCTION  int WINAPI HookGet_Change(void)

DESCRIPTION Has part of the context changed.
             Because looking for changes is not an exact science we know some
             events are always a change and some are just possible.
             Keep 2 flags.

PARAMETERS None.

RETURN     Hook change status.
*/
int WINAPI HookGet_Change(void)
{
    int Prev;

    Prev = Hook_Change;
    Hook_Change = HCHANGE_NONE;

    return(Prev);
}

```

```

/*-----
FUNCTION  HMENU WINAPI HookGet_Menu(level)

DESCRIPTION Return the handle to the current popped up menu.

PARAMETERS int level - the inverse of the menu stack level. 0=top-most

RETURN     NULL = no menu is popped up
*/
HMENU WINAPI HookGet_Menu(int level)
{
    if (level > Hook_MenuLevel) return(NULL);

    return(Hook_MenuStack[Hook_MenuLevel - level]);
}
/*-----

```

101100 5246260

FUNCTION · HMENU WINAPI HookGet_MenuAtLevel(level)
 DESCRIPTION Return the handle to the menu at the given level.
 PARAMETERS int level - the menu stack level. 0=top-most
 RETURN NULL = no menu is popped up.

```
*/
HMENU WINAPI HookGet_MenuAtLevel(int level)
{
    if (level > Hook_MenuLevel) return(NULL);

    return(Hook_MenuStack[level]);
}
```

FUNCTION int WINAPI HookGet_MenuLevel()
 DESCRIPTION Return the menu level.
 PARAMETERS None.
 RETURN The menu level : NULL = no menu is popped up.

```
*/
int WINAPI HookGet_MenuLevel()
{
    return(Hook_MenuLevel);
}
```

FUNCTION HWND WINAPI HookGet_MenuWnd(void)
 DESCRIPTION Returns the owner of the popped up window.
 Only valid if there IS a popped up menu !
 PARAMETERS None.
 RETURN Handle to the window.

```
*/
HWND WINAPI HookGet_MenuWnd(void)
{
    return(Hook_MenuhWnd);
}
```

FUNCTION static void HookMenuClear(void)
 DESCRIPTION Clear menu toggles.

2013-03-26 14:26:26

PARAMETERS None.

RETURN None.

*/

static void HookMenuClear(void)

{

if (Hook_MenuLevel == -1) return;

Hook_MenuLevel = -1; /* No popup menu. */

Hook_Change |= HCHANGE_DEFINATE;

}

/*

FUNCTION static void PASCAL HookMessage(hWnd, wParam, lParam)

DESCRIPTION Check for common context indication messages.

Use command message checker for PostMessage and SendMessage
because we never really know which will be used.

PARAMETERS HWND hWnd - Specifies the handle of the window

UINT wParam - Specifies the message

WORD lParam - Specifies 16 bits of additional
message-dependent information

LONG lParam - Specifies 16 bits of additional
message-dependent information

RETURN None.

*/

static void PASCAL HookMessage(HWND hWnd, UINT wParam, WORD lParam, LONG lParam)

{

switch (wParam)

{

/*

Menu level tracking.

*/

case WM_INITMENU:

/*

The bottom level menu is initialized.

*/

Hook_MenuhWnd = hWnd;

Hook_MenuLevel = -1;

Hook_MenuSelect = NULL;

Hook_Track = HT_NONE;

Hook_Change |= HCHANGE_DEFINATE;

break;

case WM_INITMENUPOPUP:

/*

The menu will pop up onto the screen.

NOTE: The context manager needs this to tell if a menu is up.

SORRY */

*/

parent-

last. */

```
*/
if (Hook_MenuSelect == wParam)
{
    if (Hook_MenuLevel >= MENUSTACKQTY-1) break; /*

    Hook_MenuLevel ++;
}
else
{
    /*
    ** NOTE:
    ** Of the Popup is initialized without having selected it
    ** then it is not a normal menu popup ? What do i do ?
    ** NOTE:
    ** This works for custom popups.
    */
    Hook_MenuLevel = 0; /* Don't know where this is from ?

    Hook_Track = HT_ACCEL;
}

Hook_MenuSelect = NULL;
Hook_MenuStack[Hook_MenuLevel] = wParam;
Hook_Change |= HCHANGE_DEFINATE;
break;

case WM_MENUSELECT:
/*
** Watch for the pop up menu being removed.
** or the select being moved.
** wParam = the item seelcted, (handle if popup)
** HIWORD(lParam) = our parent.
*/

if (wParam == 0 && lParam == 0xFFFFL)
{
    HookMenuClear();
    break;
}
if (Hook_MenuLevel == -1)
{
    Hook_MenuStack[++ Hook_MenuLevel] = HIWORD(lParam);
    Hook_Change |= HCHANGE_DEFINATE;
}
else
{
    if (HIWORD(lParam) == Hook_MenuSelect)
    {
        /*
        ** NOTE:
        ** This occurs if the menu select is moved back to the

        ** But the child is left on the screen ?
        */
        Hook_MenuLevel ++; /* same as
```

TOP SECRET 00000000

```
Hook_Change |= HCHANGE_DEFINATE;
    }
    else
    {
        while (Hook_MenuLevel > 0)
        {
            if (HIWORD(IParam) ==
Hook_MenuStack[Hook_MenuLevel])
                break;
            Hook_MenuLevel--;
            Hook_Change |= HCHANGE_DEFINATE;
        }
    }
}

Hook_Track = HT_NONE;
Hook_MenuSelect = wParam;
break;

case WM_SYSCOMMAND:
/*
** Check for the window being maximized, minimized or restored.
*/
switch (wParam)
{
    case SC_MAXIMIZE :
    case SC_MINIMIZE :
    case SC_RESTORE :
        Hook_Change |= HCHANGE_DEFINATE;
        break;
}

case WM_COMMAND:
/*
** Clear the menu if present.
** NOTE: Accelerator keys only exit with a WM_COMMAND
*/
if (Hook_Track == HT_ACCEL)
    HookMenuClear();
break;

case WM_ACTIVATEAPP:
/*
** We are changing applications.
*/
Hook_Change |= HCHANGE_TASK;
break;

case WM_ACTIVATE:
/*
** The window activation is changing. similar to focus.
*/
case WM_SETFOCUS:
case WM_KILLFOCUS:
/*
```

```

    /* The focus is changing.
    */
    Hook_Change |= HCHANGE_POSSIBLE;
    break;

```

```

case WM_SETTEXT:
    /*
    ** Some text is being set to a window or control.
    ** Most likely it is a change.
    */
    Hook_Change |= HCHANGE_DEFINATE;
    break;

```

```

case WM_SHOWWINDOW:
    Hook_Change |= HCHANGE_DEFINATE;
    break;

```

```

case WM_CREATE:
    /*
    ** The window is created.
    */

```

```

case WM_PAINT:
case WM_NCPAINT:
case WM_NCCALCSIZE:
case WM_CTLCOLOR:
case WM_ENTERIDLE:
    /*
    ** NOTE: It could be (Not necessary) a change.
    */
    Hook_Change |= HCHANGE_POSSIBLE;
    break;

```

```

    }

```

```

}

```

```

/*-----

```

FUNCTION **DWORD CALLBACK HookGetMsgProc(nCode, wParam, lParam)**

DESCRIPTION The HookGetMsgProc function is a callback function that the system calls whenever the GetMessage function has retrieved a message from an application queue. The system passes the retrieved message to the callback function before passing the message to the destination window procedure.

PARAMETERS **int nCode** - Specifies whether the callback function should process the message or call the CallNextHookEx function. If this parameter is less than zero, the callback function should pass the message to CallNextHookEx without further processing.

WORD wParam - Specifies a NULL value.

LPMMSG lParam - Points to an MSG structure that contains information about the message.


```

| RETURN    The callback function should return zero.
|
| */
DWORD CALLBACK HookGetMsgProc(int nCode, WORD wParam, LPMSG lpMsg)
{
    if (nCode == HC_ACTION)
    {
        HookMessage(lpMsg->hwnd, lpMsg->message, lpMsg->wParam, lpMsg->
>lpParam);
        if (lpMsg->message == WM_MOUSEMOVE)
        {
            lpMsg->wParam &= ~MK_MBUTTON;
        }
    }

    return CallNextHookEx(hGetMsgHook, nCode, wParam, (LONG)lpMsg);
}

/*-----
|
| FUNCTION    DWORD CALLBACK HookSndMsgProc(nCode, wParam, lpMsg)
|
| DESCRIPTION Hooks all SendMessage calls.
|
| PARAMETERS int nCode        -Specifies whether the callback function
|                               should process the message or call the
|                               CallNextHookEx function. If this parameter
|                               is less than zero, the callback function
|                               should pass the message to CallNextHookEx
|                               without further processing.
|
|                               WORD wParam        -Specifies whether the message is sent by
|                               the current task. This parameter is
|                               nonzero if the message is sent;
|                               otherwise, it is NULL.
|
|                               LPCALLWNDPROC lpMsg -Points to a structure that contains
|                               details about the message.
|
| RETURN     The callback function should return zero.
|
| */
DWORD CALLBACK HookSndMsgProc(int nCode, WORD wParam, LPCALLWNDPROC lpMsg)
{
    if (nCode == HC_ACTION)
    {
        HookMessage(lpMsg->hWnd, lpMsg->wMsg, lpMsg->wParam, lpMsg->lpParam);
    }
    return CallNextHookEx(hSndMsgHook, nCode, wParam, (LONG)lpMsg);
}

/*-----
|
| FUNCTION    void WINAPI HookInstall(finstall)
|
| DESCRIPTION Set up all necessary hooking code to view all messages.
|
| PARAMETERS BOOL finstall - Specifies install/uninstall toggle.

```

```

| RETURN None.
|
| */
void WINAPI HookInstall(BOOL fInstall)
{
    if (fInstall)
    { // Install only if there isn't already a hook installed
        /*
        ** Install hook for posted messages.
        */
        if (!hGetMsgHook)
            hGetMsgHook = SetWindowsHookEx(WH_GETMESSAGE,
(FARPROC)HookGetMsgProc, hInst, NULL);

        /*
        ** Install hook for sent messages.
        */
        if (!hSndMsgHook)
            hSndMsgHook = SetWindowsHookEx(WH_CALLWNDPROC,
(FARPROC)HookSndMsgProc, hInst, NULL);
    }
    else
    {
        UnhookWindowsHookEx(hGetMsgHook);
        UnhookWindowsHookEx(hSndMsgHook);
        hGetMsgHook = NULL;
        hSndMsgHook = NULL;
    }
}

```

```

/*-----
FUNCTION    BOOL WINAPI HookJournalBusy(void)

DESCRIPTION Return whether or not the DLL has a journal hook already
            installed

PARAMETERS  None.

RETURN      TRUE if journal busy.
*/
BOOL WINAPI HookJournalBusy(void)
{
    return bJournalBusy; // Is journal playback active?
}

```

<p>FUNCTION static void PlayNotify(void)</p> <p>DESCRIPTION Notify about end of playback.</p> <p>PARAMETERS None.</p>
--

| RETURN None.

*/

static void PlayNotify(void)

{

if (hWndNotify)

{

SendMessage(hWndNotify, wParamNotify, 0, 0L);

}

}

/*

FUNCTION DWORD CALLBACK PlayProc(nCode, wParam, lParam)

DESCRIPTION The PlayProc function is a callback function that a library can use to insert mouse and keyboard messages into the system message queue.

PARAMETERS int nCode - Specifies whether the callback function should process the message or call the CallNextHookEx function. If this parameter is less than zero, the callback function should pass the message to CallNextHookEx without further processing.

WORD wParam - Specifies a NULL value.

LPEVENTMSG lParam - Points to an EVENTMSG structure that represents the message being processed by the callback function.

RETURN The callback function should return a value that represents the amount of time, in clock ticks, that the system should wait before processing the message. This value can be computed by calculating the difference between the time members of the current and previous input messages. If the function returns zero, the message is processed immediately.

*/

DWORD CALLBACK PlayProc(int nCode, WORD wParam, LPEVENTMSG lParam)

{

DWORD dwRetcode = NULL;

BOOL bCallNext = TRUE;

LPRECORD lpList;

switch (nCode)

{

case HC_SKIP :

// See if we are all done playing back

if (!lpJmlList)

{

//OutputDebugString("HC_SKIP - Next event is NULL so we're all done.\n");

UnhookWindowsHookEx(hJournalHook);

PlayNotify();

bJournalBusy = FALSE;

```

// if (!wNumEvents)
//     OutputDebugString(" Played the number of events recorded.\n");
// }
// else {
//     wNumEvents--;

        lpList = lpJmlList->pNext;
        Gfree(lpJmlList);
        lpJmlList = lpList;
    }
    bCallNext = FALSE;
    break;

case HC_GETNEXT :
    // Lock and playback this member of the list.

    if (lpJmlList)
    {

        lpMsg->message = lpJmlList->msg.message;
        lpMsg->paramL = lpJmlList->msg.paramL;
        lpMsg->paramH = lpJmlList->msg.paramH;

        switch (sPlaybackSpeed)
        {
            case -1 : // Full Speed
                lpMsg->time = GetTickCount();
                dwRetcode = dwInitPlaybackTime -
GetTickCount() + GetDoubleClickTime() + 1;
                if ((long)dwRetcode < 0) // if time has gone by
                    return

                    dwRetcode = 0;
                // 0 for the wait time.
                break;

            default :
            case 0 : // Original Speed
                lpMsg->time = lpJmlList->msg.time +
dwInitPlaybackTime;

                dwRetcode = lpMsg->time - GetTickCount();
                if ((signed long)dwRetcode < 0) // if time has
                    gone by return

                    dwRetcode = 0;
                // 0 for the wait time.
                break;
        }

    }

    bCallNext = FALSE;
    break;

case HC_SYSMODALON :
    // A system modal dialog box has appeared.
    // Something bad must have happened.

```

2000-02-26 10:52:00

0070375-03404
104720" 52258260

```
// Free all remaining event structures and unhook.

// Should some sort of error message be displayed to the user when
// we receive the HC_SYSMODALOFF to say that we stopped playback?

while (lpJmlList)
{
    lpList = lpJmlList->pNext;
    Gfree(lpJmlList);
    lpJmlList = lpList;
}

UnhookWindowsHookEx(hJournalHook);
PlayNotify();
bJournalBusy = FALSE;
break;

default :
    break;
}

if (bCallNext)
{
    dwRetcode = CallNextHookEx(hJournalHook, nCode, wParam, (LONG)lpMsg);
}

return dwRetcode;
}
```

```
/*-----
FUNCTION void WINAPI Playback(hWnd, wParam, sSpeed, lpList)

DESCRIPTION Journal Playback Function

PARAMETERS HWND hWnd - Specifies handle to the window
to send notification to.
UINT wParam - Specifies notification message.
short sSpeed - Specifies speed of playback.
LPRECORD lpList - Specifies pointer to the events list.

RETURN None.
*/
void WINAPI Playback(HWND hWnd, UINT wParam, short sSpeed, LPRECORD lpList)
{
    if (bJournalBusy)
        return;

    if (lpList == NULL)
        return;

    hWndNotify = hWnd;
    wParamNotify = wParam;
    bJournalBusy = TRUE;
}
```

Figure 1. Schematic representation of the experimental design. The subjects were divided into two groups: the control group (CG) and the experimental group (EG). The CG was divided into two subgroups: the control group (CG) and the control group (CG). The EG was divided into two subgroups: the experimental group (EG) and the experimental group (EG). The subjects were divided into two groups: the control group (CG) and the experimental group (EG). The CG was divided into two subgroups: the control group (CG) and the control group (CG). The EG was divided into two subgroups: the experimental group (EG) and the experimental group (EG).

```
hJournalHook = SetWindowsHookEx(WH_JOURNALPLAYBACK, (FARPROC)PlayProc,
                                hInst, NULL);
return;
```

}

```
void WINAPI HookFreeJournal(void)
{
```

```

/*-----
FUNCTION    static void RecNotify(void)

DESCRIPTION Notify about end of recording.

PARAMETERS None.

RETURN     None.
*/

```

```
static void RecNotify(void)
{
    LPRECORD lpList;
    DWORD dwFirstTime;

    // reset the time field in all of these
    if (lpJmllList)
        dwFirstTime = lpJmllList->msg.time;

    lpList = lpJmllList;
```

```
while (lpList != NULL)
{
    lpList->msg.time -= dwFirstTime;
    lpList = lpList->pNext;
}

SendMessage(hWndNotify, wParamNotify, 0, (LONG)lpJmlList);
```

}

FUNCTION **DWORD CALLBACK RecProc(nCode, wParam, lParam)**

DESCRIPTION The RecProc function is a callback function that records messages that the system removes from the system message queue.

PARAMETERS **int nCode** - Specifies whether the callback function should process the message or call the CallNextHookEx function. If this parameter is less than zero, the callback function should pass the message to CallNextHookEx without further processing.

WORD wParam - Specifies a NULL value.

LONG lParam - Points to an EVENTMSG structure that represents the message being processed by the callback function.

RETURN The callback function should return zero.

```

*/
DWORD CALLBACK RecProc(int nCode, WORD wParam, LONG lParam)
{
    static LPRECORD lpPrevList; // Handle to prev recorded event
    static WORD wNumEvents; // ** number of events recorded ** for testing **
    static BOOL bPause = FALSE;
    LPRECORD lpList;
    LPEVENTMSG lpEvent;
    BOOL bCallNext = TRUE;
    DWORD dwRetcode = 0;
    DWORD dwTime;

    switch (nCode)
    {
        case HC_ACTION :
            if (bPause)
            {
                break;
            }
            dwTime = GetTickCount();
            lpEvent = (LPEVENTMSG) lParam;
            if (lpEvent->message == WM_KEYDOWN && LOBYTE(lpEvent-
>paramL) == wStopKey)
            {

```

```

HookFreeJournal();
RecNotify();
break;
}
if (lpEvent->message >= WM_MOUSEFIRST && lpEvent->message <=
WM_MOUSELAST)
{
    if (wMouRec == REC_MOUSEIGNORE)
    {
        break;
    }
    else if (wMouRec == REC_MOUSECLICK && lpEvent-
>message == WM_MOUSEMOVE)
    {
        break;
    }
}
// Allocate the next member (zeroinit it so hNext field doesn't
// have to be explicitly set to zero)
lpList = Gmalloc((DWORD) sizeof(RECORD));

if (lpList == NULL)
{
    HookFreeJournal();
    RecNotify();
    break;
}

// Update the previous member to point to this new one.
if (lpJmlList == NULL)
{ // It's the first one
    wNumEvents = 0;
    lpJmlList = lpList;
}
else
{
    lpPrevList->pNext = lpList;
}
lpPrevList = lpList;

// Store the message in the new one

lpList->msg = *lpEvent;
lpList->msg.time = dwTime;
break;

case HC_SYSMODALON:
    bPause = TRUE;
    break;

case HC_SYSMODALOFF:
    bCallNext = FALSE;
    bPause = FALSE;
    HookFreeJournal();
    RecNotify();
    break;

```

00703230=00404


```

        default :
            break;
    }

    if (bCallNext) {
        dwRetcode = CallNextHookEx(hJournalHook, nCode, wParam, lParam);
    }
    return dwRetcode;
}

```

```

/*-----
FUNCTION    void WINAPI Record(hWnd, wParam, wKey, wMou)

DESCRIPTION Journal Record Function

PARAMETERS HWND hWnd      - Specifies handle to the window
                        to send notification to.
        UINT wParam      - Specifies notification message.
        UINT wKey        - Specifies stop key VK_ value.
        UINT wMou        - Specifies type of mouse events that
                        should be recorded.

RETURN      None.
*/
void WINAPI Record(HWND hWnd, UINT wParam, UINT wKey, UINT wMou)
{

```

```

    if (bJournalBusy)
        return;

```

```

    hWndNotify = hWnd;
    wParamNotify = wParam;
    wStopKey = wKey;
    wMouRec = wMou;
    lpJmlList = NULL;

```

```

    hJournalHook = SetWindowsHookEx(WH_JOURNALRECORD, (FARPROC)RecProc,
hInst, NULL);

```

```

    if (hJournalHook)
        bJournalBusy = TRUE;

```

```

}

```

TOP SECRET

```

*/
else
{
    switch (iScrCom & SCRLS_ACT)
    {
        case SB_LINEUP:
            /* line up
            */
            idWord = IDW_LINEUP;
            break;
        case SB_LINEDOWN:
            /* line down
            */
            idWord = IDW_LINEDOWN;
            break;
        case SB_PAGEUP:
            /* page up
            */
            idWord = IDW_PAGEUP;
            break;
        case SB_PAGEDOWN:
            /* page down
            */
            idWord = IDW_PAGEDOWN;
            break;
    }
}
/* MDI frame is a special case
*/
if (iScrCom & SCRLS_MDI )
{
    len = wprintf(
        szCaptionBuf, "%s %s",
        (LPSTR)UserGetDefWord(IDW_MDIFRAME),
        (LPSTR)UserGetDefWord(idWord));
}
else
{
    lstrcpy(szCaptionBuf, UserGetDefWord(idWord));
    len = lstrlen(szCaptionBuf);
}
return(len);
}

```

```

#ifdef DEBUG_DLG

```

```

/*-----
FUNCTION   _LOCAL int ContextPakWindDebug(hwnd)
DESCRIPTION Get debug information for the given window.
PARAMETERS HWND hwnd - Specifies handle to the window we are looking at.
RETURN    Length of the caption text.

```

```

1
*/
LOCAL int ContextPakWindDebug(HWND hwnd)
{
    /* Now we can recieve text from EDIT
    */
    return((int) SendMessage(hwnd, WM_GETTEXT, sizeof(szCaptionBuf) - 1,
(LONG)(LPSTR)szCaptionBuf));
}

```

```

FUNCTION    _LOCAL int ContextPakDebug(void)

DESCRIPTION Create debug string.

PARAMETERS None.

RETURN      Length of the caption text.
*/
_LOCAL int ContextPakDebug(void)
{
    /* ADD DEBUG INFO TO THE CONTEXT STRING
    */
    HWND hwnd = pciLast->hwnd;
    PSTR Str;
    int len = strlen(szCaptionBuf);
    int lend;

    if (! len)
    {
        switch (pciLast->conType)
        {
            case CON_WINDOW:
            case CON_ICON:
                /* Add window debug info
                */
                len = ContextPakWindDebug(hwnd);
                break;

            default:
                ;
        }
    }

    if (! len)
    {
        /* No text for this item
        */
        strcpy(szCaptionBuf, "<No Caption>");
        len = strlen(szCaptionBuf);
    }
}

```

```

/* Move start pointer
*/
Str = szCaptionBuf + len;

/* Show the handle and the parent handle for the related window.
*/
lend = wsprintf(Str, "\\t%1d %04X\\t", pciLast->iLevel, hwnd);
Str += lend;

/* Add debug info to the string.
*/
switch (pciLast->conType)
{
    case CON_WIND:
    case CON_ICON:
        /* Its a window or a control.
        */
        if (! hwnd)
            /* No associated window ?
            */
            break;

        /* Parent and owner
        */
        lend = wsprintf(Str, "%04X %04X ", GetParent(hwnd), GetWindow(hwnd,
GW_OWNER));

        /* Add the class name to it.
        */
        GetClassName(hwnd, Str+lend, MAXSTRING);

        /* Usefull properties
        */
        if (! IsWindowEnabled(hwnd))
            lstrcat(Str, " <INACTIVE>");
        else if (! IsWindowVisible(hwnd))
            lstrcat(Str, " <INVISIBLE>");
        else if (IsZoomed(hwnd))
            lstrcat(Str, " <MAXIMIZED>");
        else if (IsIconic(hwnd))
            lstrcat(Str, " <MINIMIZED>");
        if (hwnd == GetActiveWindow())
            lstrcat(Str, " <ACTIVE>");
        if (hwnd == GetFocus())
            lstrcat(Str, " <FOCUS>");

        /* We need to return this
        */
        lend = lstrlen(Str);
        break;

    case CON_SYSCOM:
        /* System commans
        */
        lend = wsprintf(Str, "<SYSTEM COMMAND %d>", pciLast->u.SysCom);

```

```

        break;

    case CON_MENUPOPUP:
        /* Popup menu properties
        */
        lend = wsprintf(Str, "%04x <POPUP MENU %d>",
            GetMenuState(pciLast->u.MenuPop.hMenu, pciLast-
>u.MenuPop.iEntry,
                MF_BYPOSITION), pciLast->u.MenuPop.iEntry);
        break;

    case CON_MENU:
        /* Menu item properties
        */
        lend = wsprintf(Str, "<MENU ITEM %d>", pciLast->u.Menu.id);
        break;

    case CON_ACCEL:
        /* Accelerator
        */
        lend = wsprintf(Str, "<ACCELERATOR FOR %d>", pciLast->u.Acc.id);
        break;

    case CON_LAUNCH:
        /* ProgMan launch command
        */
        lend = wsprintf(Str, "<%s>", (LPSTR)(pciLast->u.PMItem.szFile));
        break;

    case CON_MACRO:
        /* Macro
        */
        lend = wsprintf(Str, "<MACRO>");
        break;
    }

    /* Calculate maximum length
    */
    if (lend > iDebugCapLen)
        iDebugCapLen = lend;

    return(len);
}

#endif

```

```

/*-----
FUNCTION  _LOCAL int ContextPak(void)

DESCRIPTION Build a context string for the context block.
            User pciLast to identify the object.

PARAMETERS None.

RETURN    Length of the caption text.

```

0078333-03440

```
/*  
** File: PLAYBACK.C  
**  
** Functions for Macro Execution  
**  
** Public functions:  MakeHookReady  
**                   VCM_Execute  
**  
** Private Functions : me_SingleCommand  
**                   me_Click  
**                   me_Key  
**                   me_String  
**                   me_Execute
```

```
#define WIN32 // need this to use extended 3.1 functionality
#include <windows.h>
```

```
#include <shellapi.h>
#include <ctype.h>
```

```
#include "vtools.h"
#include "vc.h"
```

```
/* Private Function Prototypes
```

```

_LOCAL BOOL me_SingleCommand(LPMACRO, HWND);
_LOCAL BOOL me_Clk(LPMACRO);
_LOCAL BOOL me_Key(VCM_KEY KeyType);
_LOCAL BOOL me_String(LPSTR Str);
_LOCAL BOOL me_Execute(LPSTR Str);

```

```

/*
FUNCTION    BOOL MakeHookReady(void)

DESCRIPTION Wait until we finish playback.

PARAMETERS None.

RETURN     TRUE if success.
*/

```

```

BOOL MakeHookReady(void)
{
    MSG msg;

    while (HookJournalBusy())
    {
        if (PeekMessage(&msg, NULL, NULL, NULL, PM_REMOVE))
            ProcessMessage(msg);
    }
}

```

	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100																																																																																																																																																																																																																																																																																																																																																																																																											
0	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P	0Q	0R	0S	0T	0U	0V	0W	0X	0Y	0Z	0[0\	0]	0^	0_	0`	0'	0(0)	0*	0+	0,	0-	0.	0:	0;	0<	0=	0>	0?	0@	0A	0B	0C	0D	0E	0F	0G	0H	0I	0J	0K	0L	0M	0N	0O	0P

BOOL VCM_Execute(LPCTSTR CmdPtr, HWND hGlobalWnd)

FUNCTION _LOCAL BOOL me_SingleCommand(LPMACRO CmdPtr, HWND hWnd)

DESCRIPTION Execute single macro command.

```

PARAMETERS LPMACRO CmdPtr - Points to an list of MACRO elements.
           HWND hGlobalWnd - Default window to send commands to.

RETURN TRUE if success.
*/
_LOCAL BOOL me_SingleCommand(LPMACRO CmdPtr, HWND hWnd)
{
    RECT rect;
    POINT pt;

    BOOL bFoundIt;
    HMENU hMenu;
    WORD wTotal, wFlags, i, KeyPos;
    MACRO macro;
    WORD wKeyUp, wKeyDown;
    int iLevel;

    /* Was a specific window given or are we to assume that we should use
    ** the currently active window?
    */
    if (! hWnd)
        hWnd = GetActiveWindow();

    /* Make sure it is a valid window handle
    */
    if (! IsWindow(hWnd))
        return FALSE;

    /* Was a class specified and if so was there also window text given.
    ** Don't allow specification of window text without the window
    ** class being given as well.
    */

    /* Determine the type of command and process the command specific action.
    */
    switch (CmdPtr->cmdType)
    {
        case CMD_MENU :
            /* Verify that the given window has a menu (do I need to bother w/this?)
            */
            if (!(hMenu = GetMenu(hWnd)))
                return FALSE;
            /* Check to make sure selection is available
            */
            i = GetMenuState(hMenu, CmdPtr->Cmd.Menu.id, MF_BYCOMMAND);
            if ((i & MF_DISABLED) || (i & MF_GRAYED) || (i == -1))
                break;

            /* Clear the menus before the command is sent
            */
            iLevel = HookGet_MenuLevel();
            while (iLevel-- >= 0)
            {
                PostMessage(hWnd, WM_SYSKEYDOWN, VK_ESCAPE, 0L);
                Yield();
            }
        }
    }
}

```



```

    }

    PostMessage(hWnd, WM_COMMAND, CmdPtr->Cmd.Menu.id, 0L);
    break;

case CMD_MENUPOPUP :
    /* Verify that the given window has a menu (do I need to bother w/this?)
    */
    if (!(hMenu = GetMenu(hWnd)))
        return FALSE;
    /* Test to see where the current menu highlighting is.
    */
    hMenu = HookGet_MenuAtLevel(0);

    /* No menu up - Activate the Menu Bar
    */
    if (!hMenu)
    {
        hMenu = GetMenu(hWnd);
        PostMessage(hWnd, WM_SYSCOMMAND, SC_KEYMENU,
0L);

        i = CmdPtr->Cmd.MenuPopup.iKeyPos;
        while (i--)
        {
            PostMessage(hWnd, WM_SYSKEYDOWN, VK_RIGHT,
0L);

            Yield();
        }

        /* Need to check to see if there really is a menu to pop up or
        ** if it is a menu item on the menu bar that has no pulldown.
        */
        if ((i = GetMenuItemID(hMenu, CmdPtr-
>Cmd.MenuPopup.iKeyPos)) != -1)
        {
            iLevel = HookGet_MenuLevel();
            while (iLevel-- >= 0)
            {
                PostMessage(hWnd, WM_SYSKEYDOWN,
VK_ESCAPE, 0L);

                Yield();
            }

            PostMessage(hWnd, WM_COMMAND, i, 0L);
        }
        else
            PostMessage(hWnd, WM_SYSKEYDOWN,
VK_DOWN, 0L);
    }
    /* It's a cascading popup
    */
    else
    {
        /* Pop "back" the menus to the correct level
        */

```

00789395440
1012052660

VK_ESCAPE, 0L);

>Cmd.MenuPopup.wLevel);

MF_SEPARATOR)))

wKeyDown, 0L);

```
while(HookGet_Menu(CmdPtr->Cmd.MenuPopup.wLevel + 1))
{
    PostMessage(hWnd, WM_SYSKEYDOWN,
        Yield());
}

/* Get the current position that is hilited
*/
hMenu = HookGet_MenuAtLevel(CmdPtr-
wTotal = GetMenuItemCount(hMenu);

i = 0;
KeyPos = 0;
bFoundIt = FALSE;
while ((i < wTotal) && !bFoundIt)
{
    wFlags = GetMenuState(hMenu, i, MF_BYPOSITION);
    if (wFlags & MF_HILITE)
        bFoundIt = TRUE;
    else
    {
        if ((wFlags & MF_POPUP) || !(wFlags &
            KeyPos++;
            i++;
        }
    }

/* Must take separators into account in position
*/
i = KeyPos;

if (CmdPtr->Cmd.MenuPopup.wLevel)
{
    wKeyUp      = VK_UP;
    wKeyDown    = VK_DOWN;
}
else
{
    wKeyUp      = VK_LEFT;
    wKeyDown    = VK_RIGHT;
}

if (i < (WORD)CmdPtr->Cmd.MenuPopup.iKeyPos)
{
    i = CmdPtr->Cmd.MenuPopup.iKeyPos - i;
    while (i-->0)
    {
        PostMessage(hWnd, WM_SYSKEYDOWN,
            wKeyUp, 0L);
        PostMessage(hWnd, WM_SYSKEYDOWN,
            wKeyDown, 0L);
    }
}
else
{
    PostMessage(hWnd, WM_SYSKEYDOWN,
        wKeyUp, 0L);
    PostMessage(hWnd, WM_SYSKEYDOWN,
        wKeyDown, 0L);
}
```

```

        if (i > (WORD)CmdPtr->Cmd.MenuPopup.iKeyPos)
        {
            i = i - CmdPtr->Cmd.MenuPopup.iKeyPos;
            while (i-->0)
            {
                PostMessage(hWnd,
WM_SYSKEYDOWN, wKeyUp, 0L);
            }
        }

        PostMessage(hWnd, WM_SYSKEYDOWN, VK_RETURN, 0L);
    }

    break;

case CMD_SYSTEM :
    if ((CmdPtr->Cmd.System.wCmd == SC_KEYMENU) || (CmdPtr-
>Cmd.System.wCmd == SC_MOUSEMENU))
    {
        /* Activating the system menu of an iconized window can't be
done
        ** with the normal syscommands and syskeys.
effect
        ** Using mouse commands works but it has the unpleasant side
acceptable
        ** of moving the pointer. Therefore this may not be an
        ** solution.
        */
        if (GetParent(hWnd))
        {
            /* This combination seems to work in all cases except
            ** the system menu of a child window in Excel that is
            */
            PostMessage(hWnd, WM_SYSCOMMAND, CmdPtr-
PostMessage(hWnd, WM_SYSKEYDOWN,
VK_RETURN, 0L);
        }
        else
        {
            PostMessage(hWnd, WM_SYSCOMMAND,
SC_KEYMENU, 0L);
            PostMessage(hWnd, WM_SYSKEYDOWN,
VK_SPACE, 0L);
        }
    }
    else
    {
        iLevel = HookGet_MenuLevel();
        while (iLevel-- >= 0)
        {

```

TOP SECRET - SENSITIVE

```

VK_ESCAPE, 0L);
        PostMessage(hWnd, WM_SYSKEYDOWN,
        Yield();
    }

    PostMessage(hWnd, WM_SYSCOMMAND, CmdPtr-
>Cmd.System.wCmd, 0L);
    }

    break;

    case CMD_MESSAGE :
        /* Just message to post
        */
        PostMessage(hWnd, CmdPtr->Cmd.Msg.wMsg, CmdPtr-
>Cmd.Msg.wParam,
        CmdPtr->Cmd.Msg.lParam);
        break;

    case CMD_SELECT :
    {
        /* Bring hWnd to the top and activate it.
        */
        POINT pt;
        int i;

        if (GetWindowLong(hWnd, GWL_STYLE) & WS_CHILD)
        {
            SetFocus(hWnd);
            GetWindowRect(hWnd, &rect);

            pt.x = rect.left;
            pt.y = rect.top;
            for (i = 0; i < 5; i++)
            {
                if (WindowFromPoint(pt) == hWnd)
                    break;
                pt.x++;
                pt.y++;
            }
            macro.cmdType = CMD_MOUSE;
            macro.pNext = NULL;
            macro.szWndClass = NULL;
            macro.szDesc = NULL;
            macro.Cmd.Mouse.mouType = MOU_LBCLK;
            macro.Cmd.Mouse.bPosType = VCM_MP_SCREEN;
            macro.Cmd.Mouse.wX = pt.x;
            macro.Cmd.Mouse.wY = pt.y;
            macro.Cmd.Mouse.CtrlPressed = 0;
            macro.Cmd.Mouse.ShiftPressed = 0;
            macro.Cmd.Mouse.AltPressed = 0;

            VCM_Execute(&macro, hWnd);
        }
        else
        {
            BringWindowToTop(hWnd);

```

104720-9366260

```

    }
    break;
}

```

```

/* Mouse, Keyboard, and Journal Playback commands will all be handled via
** a Journal Playback Hook. We still need to go through the window
** checking above to make sure that if the events are to go to a specific
** window that the window is there.
*/

```

```

case CMD_MOUSE :

```

```

    /* For all mouse commands, convert any client coordinates
    ** to screen coordinates before proceeding further.
    */
    if (CmdPtr->Cmd.Mouse.bPosType == VCM_MP_CLIENT)
    {
        pt.x = CmdPtr->Cmd.Mouse.wX;
        pt.y = CmdPtr->Cmd.Mouse.wY;
        ClientToScreen(hWnd, (LPPOINT) &pt);
        CmdPtr->Cmd.Mouse.wX = pt.x;
        CmdPtr->Cmd.Mouse.wY = pt.y;
        /* in case it's used later
        */
        CmdPtr->Cmd.Mouse.bPosType = VCM_MP_SCREEN;
    }

```

```

    switch (CmdPtr->Cmd.Mouse.mouType)
    {

```

```

        case MOU_MOVE :

```

```

            /* Do moves need to be done via playback or is this

```

OK???

```

            */

```

```

            SetCursorPos(CmdPtr->Cmd.Mouse.wX, CmdPtr->

```

>Cmd.Mouse.wY);

```

            break;

```

```

        /* Is it necessary to set the focus for clicks and double clicks?
        */

```

```

        case MOU_LDBLCLK : // Double Clicks

```

```

        case MOU_RDBLCLK :

```

```

        case MOU_MDBLCLK :

```

```

        case MOU_LBCLK : // Single Clicks

```

```

        case MOU_RBCLK :

```

```

        case MOU_MBCLK :

```

```

            return (me_Clk(CmdPtr));

```

```

            break;

```

```

        }

```

```

        break;

```

```

case CMD_KEY :

```

```

    /* May need more values passed in for the OEM scan code to be set.

```

```

    ** Is it necessary to set the focus here before the key is sent?

```

FORN-922200

```

    /* if window is iconized or ALT is pressed then WM_SYSKEY
    */
    return (me_Key(CmdPtr->Cmd.Key));

    break;

case CMD_TEXT :

    return (me_String(CmdPtr->szDesc));

    break;

case CMD_LAUNCH :

    return (me_Execute(CmdPtr->szDesc));

    break;

case CMD_JOURNAL :
{
    LPRECORD pFirstRecord;
    LPRECORD pRecord;
    POINT pt;

    if (HookJournalBusy())
        return FALSE;

    /* need to define how the playback list is going to be sent and what
    /* we are going to do about any timing type problems such as windows
    /* taking longer to appear than they did in the original recording etc.
    */
    pFirstRecord = RecordMake(CmdPtr->Cmd.Journal.pRecord);
    for (pRecord = pFirstRecord; pRecord != NULL; pRecord = pRecord-
    >pNext)
    {
        if (pRecord->msg.message >= WM_MOUSEFIRST &&
        pRecord->msg.message <= WM_MOUSELAST)
        {
            pt.x = pRecord->msg.paramL;
            pt.y = pRecord->msg.paramH;
            ClientToScreen(hWnd, &pt);
            pRecord->msg.paramL = pt.x;
            pRecord->msg.paramH = pt.y;
        }
    }
    Playback(NULL, 0, 0, pFirstRecord);
    break;
}

default :
    /* error - Unknown Command Type
    */
    return FALSE;
    break;
}

```

00703725-01404
T01T00-927000

```

    return TRUE;
}

```

```

#define MAKEKEY(uVKey) (MAKEDWORD(uVKey, MapVirtualKey(uVKey, 0)))

```

```

/*-----
FUNCTION  _LOCAL BOOL me_Clk(LPMACRO CmdPtr)
DESCRIPTION Execute mouse macro command.
PARAMETERS LPMACRO CmdPtr  - Points to an list of MACRO elements.
RETURN    TRUE if success.
*/
_LOCAL BOOL me_Clk(LPMACRO CmdPtr)
{
    LPRECORD lpList, lpHead;
    WORD  Down, DownSec, Up;
    WORD  time = 0x50;
    BOOL  bSysKey = (CmdPtr->Cmd.Mouse.AltPressed) && ! (CmdPtr->Cmd.Mouse.CtrlPressed);
    POINT ptCur;

    GetCursorPos(&ptCur);

    /* Mouse coordinates have already been converted to screen coordinates
    */
    switch (CmdPtr->Cmd.Mouse.mouType)
    {
        case MOU_LBCLK :
            Down = WM_LBUTTONDOWN;
            DownSec = NULL;
            Up = WM_LBUTTONUP;
            break;
        case MOU_RBCLK :
            Down = WM_RBUTTONDOWN;
            DownSec = NULL;
            Up = WM_RBUTTONUP;
            break;
        case MOU_MBCLK :
            Down = WM_MBUTTONDOWN;
            DownSec = NULL;
            Up = WM_MBUTTONUP;
            break;
        case MOU_LBDBCLK :
            Down = WM_LBUTTONDOWN;
            DownSec = WM_LBUTTONDBLCLK;
            Up = WM_LBUTTONUP;
            break;
        case MOU_RBDBCLK :
            Down = WM_RBUTTONDOWN;
            DownSec = WM_RBUTTONDBLCLK;
    }
}

```

"32456789"

```

        Up = WM_RBUTTONDOWNUP;
        break;
    case MOU_MBDLCLK :
        Down = WM_MBUTTONDOWN;
        DownSec = WM_MBUTTONDOWNBLCLK;
        Up = WM_MBUTTONDOWNUP;
        break;
    default:
        return FALSE;
}

lpList = Gmalloc((DWORD) sizeof(RECORD));
lpHead = lpList;

if (lpList)
{
    lpList->msg.message = WM_MOUSEMOVE;
    lpList->msg.paramL = CmdPtr->Cmd.Mouse.wX;
    lpList->msg.paramH = CmdPtr->Cmd.Mouse.wY;
    lpList->msg.time = time;
    time += 0x50;
}
else
    return FALSE;

if (CmdPtr->Cmd.Mouse.AltPressed)
{
    lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));
    if (lpList->pNext)
    {
        lpList = lpList->pNext;
        lpList->msg.message = WM_SYSKEYDOWN;
        lpList->msg.paramL = MAKEKEY(VK_MENU);
        lpList->msg.paramH = 0x1; // repeat count
        lpList->msg.time = time;
        time += 0x50;
    }
    else
        return FALSE;
}

if (CmdPtr->Cmd.Mouse.CtrlPressed)
{
    lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

    if (lpList->pNext)
    {
        lpList = lpList->pNext;
        lpList->msg.message = WM_KEYDOWN;
        lpList->msg.paramL = MAKEKEY(VK_CONTROL);
        lpList->msg.paramH = 0x1; // repeat count
        lpList->msg.time = time;
        time += 0x50;
    }
    else

```

10112010-00000000


```

        return FALSE;
    }

    if (CmdPtr->Cmd.Mouse.ShiftPressed)
    {
        IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (IpList->pNext)
        {
            IpList = IpList->pNext;
            IpList->msg.message = bSysKey ? WM_SYSKEYDOWN :
WM_KEYDOWN;
            IpList->msg.paramL = MAKEKEY(VK_SHIFT);
            IpList->msg.paramH = 0x1; // repeat count
            IpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

    if (IpList->pNext)
    {
        IpList = IpList->pNext;
        IpList->msg.message = Down;
        IpList->msg.paramL = CmdPtr->Cmd.Mouse.wX;
        IpList->msg.paramH = CmdPtr->Cmd.Mouse.wY;
        IpList->msg.time = time;
        time += 0x50;
    }
    else
        return FALSE;

    if (DownSec)
    {
        IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (IpList->pNext)
        {
            IpList = IpList->pNext;
            IpList->msg.message = Up;
            IpList->msg.paramL = CmdPtr->Cmd.Mouse.wX;
            IpList->msg.paramH = CmdPtr->Cmd.Mouse.wY;
            IpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;

        IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (IpList->pNext)
        {

```

00793303 004404

09393E-0040
F04F2E05A2E8260

```
        IpList = IpList->pNext;
        IpList->msg.message = DownSec;
        IpList->msg.paramL = CmdPtr->Cmd.Mouse.wX;
        IpList->msg.paramH = CmdPtr->Cmd.Mouse.wY;
        IpList->msg.time = time;
        time += 0x50;
    }
    else
        return FALSE;
}
IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

if (IpList->pNext)
{
    IpList = IpList->pNext;
    IpList->msg.message = Up;
    IpList->msg.paramL = CmdPtr->Cmd.Mouse.wX;
    IpList->msg.paramH = CmdPtr->Cmd.Mouse.wY;
    IpList->msg.time = time;
    time += 0x50;
}
else
    return FALSE;

if (CmdPtr->Cmd.Mouse.ShiftPressed)
{
    IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

    if (IpList->pNext)
    {
        IpList = IpList->pNext;
        IpList->msg.message = bSysKey ? WM_SYSKEYUP : WM_KEYUP;
        IpList->msg.paramL = MAKEKEY(VK_SHIFT);
        IpList->msg.paramH = 0x1; // repeat count
        IpList->msg.time = time;
        time += 0x50;
    }
    else
        return FALSE;
}

if (CmdPtr->Cmd.Mouse.CtrlPressed)
{
    IpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

    if (IpList->pNext)
    {
        IpList = IpList->pNext;
        IpList->msg.message = WM_KEYUP;
        IpList->msg.paramL = MAKEKEY(VK_CONTROL);
        IpList->msg.paramH = 0x1; // repeat count
        IpList->msg.time = time;
        time += 0x50;
    }
    else
        return FALSE;
}
```

0079372E-004404

```
        return FALSE;
    }

    if (CmdPtr->Cmd.Mouse.AltPressed)
    {
        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = WM_KEYUP;
            lpList->msg.paramL = MAKEKEY(VK_MENU);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

    if (lpList->pNext)
    {
        lpList = lpList->pNext;
        lpList->msg.message = WM_MOUSEMOVE;
        lpList->msg.paramL = ptCur.x;
        lpList->msg.paramH = ptCur.y;
        lpList->msg.time = time;
        time += 0x50;
    }
    else
        return FALSE;

    if (! MakeHookReady())
        return FALSE;
    else
        Playback(NULL, 0, -1, lpHead);

    return TRUE;
}

/*-----
FUNCTION  _LOCAL BOOL me_Key(KeyType)
DESCRIPTION Execute key macro command.
PARAMETERS VCM_KEY KeyType - Specifies ke description struct.
RETURN    TRUE if success.
*/
_LOCAL BOOL me_Key(VCM_KEY KeyType)
{
```

```
LPRECORD lpList, lpHead;
WORD    time = 0x50;
BOOL    bSysKey = (KeyType.AltPressed) && ! (KeyType.CtrlPressed);
POINT   ptCur;
```

```
GetCursorPos(&ptCur);
```

```
/* Not quite sure why something like a mouse move must be sent
** before the key down to have the key down be recognized.
*/
```

```
lpList = Gmalloc((DWORD) sizeof(RECORD));
```

```
lpHead = lpList;
```

```
if (lpList)
```

```
{
```

```
    lpList->msg.message = WM_MOUSEMOVE;
```

```
    lpList->msg.paramL = ptCur.x;
```

```
    lpList->msg.paramH = ptCur.y;
```

```
    lpList->msg.time = time;
```

```
    time += 0x50;
```

```
}
```

```
else
```

```
    return FALSE;
```

```
if (KeyType.AltPressed)
```

```
{
```

```
    lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));
```

```
    if (lpList->pNext)
```

```
    {
```

```
        lpList = lpList->pNext;
```

```
        lpList->msg.message = WM_SYSKEYDOWN;
```

```
        lpList->msg.paramL = MAKEKEY(VK_MENU);
```

```
        lpList->msg.paramH = 0x1; // repeat count
```

```
        lpList->msg.time = time;
```

```
        time += 0x50;
```

```
    }
```

```
    else
```

```
        return FALSE;
```

```
}
```

```
if (KeyType.CtrlPressed)
```

```
{
```

```
    lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));
```

```
    if (lpList->pNext)
```

```
    {
```

```
        lpList = lpList->pNext;
```

```
        lpList->msg.message = WM_KEYDOWN;
```

```
        lpList->msg.paramL = MAKEKEY(VK_CONTROL);
```

```
        lpList->msg.paramH = 0x1; // repeat count
```

```
        lpList->msg.time = time;
```

```
        time += 0x50;
```

```
    }
```

```
    else
```

```

        return FALSE;
    }

    if (KeyType.ShiftPressed)
    {
        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = bSysKey ? WM_SYSKEYDOWN :
WM_KEYDOWN;

            lpList->msg.paramL = MAKEKEY(VK_SHIFT);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    if (KeyType.cKey)
    {
        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = bSysKey ? WM_SYSKEYDOWN :
WM_KEYDOWN;

            lpList->msg.paramL = MAKEKEY(KeyType.cKey);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;

        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = bSysKey ? WM_SYSKEYUP : WM_KEYUP;
            lpList->msg.paramL = MAKEKEY(KeyType.cKey);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    if (KeyType.ShiftPressed)
    {

```

2012-09-20 14:20:00

```

        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = bSysKey ? WM_SYSKEYUP : WM_KEYUP;
            lpList->msg.paramL = MAKEKEY(VK_SHIFT);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    if (KeyType.CtrlPressed)
    {
        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = WM_KEYUP;
            lpList->msg.paramL = MAKEKEY(VK_CONTROL);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    if (KeyType.AltPressed)
    {
        lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

        if (lpList->pNext)
        {
            lpList = lpList->pNext;
            lpList->msg.message = (
                ! (KeyType.cKey) ||
                ! (KeyType.CtrlPressed) ||
                ! (KeyType.ShiftPressed)
            ) ? WM_SYSKEYUP : WM_KEYUP;
            lpList->msg.paramL = MAKEKEY(VK_MENU);
            lpList->msg.paramH = 0x1; // repeat count
            lpList->msg.time = time;
            time += 0x50;
        }
        else
            return FALSE;
    }

    if (! MakeHookReady())
        return FALSE;
    else

```

00000000-00000000-00000000-00000000

Playback(NULL, 0, -1, lpHead);

return TRUE;

}

/*-----

FUNCTION _LOCAL BOOL me_String(LPSTR Str)

DESCRIPTION Execute string macro command.

PARAMETERS LPSTR Str - Specifies source string.

RETURN TRUE if success.

*/

_LOCAL BOOL me_String(LPSTR Str)

{

LPRECORD lpList, lpHead;

POINT ptCur;

LONG time=0x50;

if (Str == NULL)
return FALSE;

GetCursorPos(&ptCur);

/* Not quite sure why something like a mouse move must be sent
** before the key down to have the key down be recognized.

*/

lpList = Gmalloc((DWORD) sizeof(RECORD));

lpHead = lpList;

if (lpList)
{
lpList->msg.message = WM_MOUSEMOVE;
lpList->msg.paramL = ptCur.x;
lpList->msg.paramH = ptCur.y;
lpList->msg.time = 0x50;

}
else

return FALSE;

while (*Str != NULL)

{

if (isupper(*Str))

{

lpList->pNext = Gmalloc((DWORD) sizeof(RECORD));

if (lpList->pNext)

{

lpList = lpList->pNext;

lpList->msg.message = WM_KEYDOWN;

lpList->msg.paramL = MAKEKEY(VK_SHIFT);

Playback(NULL, 0, -1, lpHead);

```
return TRUE;
```

}

```

/*
FUNCTION    _LOCAL BOOL me_Execute(LPSTR Str)
DESCRIPTION Execute launch macro command.
PARAMETERS LPSTR Str - Specifies command string
RETURN      TRUE if success.
*/

```

```
_LOCAL BOOL me_Execute(LPSTR Str)  
{
```

```
char szExec[MAXFILENAME + 1];
char * pszParam;
```

```

Istrcpy(szExec, Str);
for (pszParam = szExec; *pszParam != '\0' ; pszParam ++)
{

```

```
if (*pszParam == ' ')
```

```
{
    *pszParam = '\0';
    pszParam++;
    break;
}
```

```

}
if (ShellExecute(NULL, NULL, (LPSTR)szExec, (LPSTR)pszParam, NULL,
HOWNORMAL) < 32)

```

```
{
    Error(ERRAppExec, (LPSTR)Str);
    return FALSE;
}
```

```
return TRUE;
```

}

[illegible]


```

IDM_PREFS = MENU_STATUS,
IDM_TRAIN,
IDM_EDIT,
IDM_PAUSE,
IDM_EXIT,
IDM_HELPCONTENT,
IDM_HELPSEARCH,
IDM_HELPONHELP,
IDM_ABOUT
};

/*-----
|
| Strings
|
*/
enum
{
    IDS_TITLE = IDS_STATUS,
    IDS_DEBUG,
    IDS_PAUSE,
    IDS_CONFID,
    IDS_VOLUME,
    IDS_NEW,
    IDS_QUERY
};

/*-----
|
| System menu additions. NOTE: leave low 4 bits unused !
|
*/
#define IDM_SYSDEBUG    (0x0110)

/*-----
|
| Communucation with Editor
|
*/
_LOCAL char szFrameClass[] = "VoiceEditFrame";
_LOCAL UINT iEditChangeMsg = NULL;

_LOCAL char szStatusClass[] = "VoiceStatus";

_LOCAL HWND hwndStatus = NULL;
_LOCAL HWND hwndList = NULL;

_LOCAL HANDLE hAccTableStatus;

_LOCAL WORD PhraseTimer = NULL;

_LOCAL int iVolumeMin = 20;
_LOCAL int iVolumeMax = 80;

_LOCAL UINT wCloseCallInc = 0;

```

```

_LOCAL BOOL bCloseCallWas = FALSE;
_LOCAL UINT wCloseCallNumber;
_LOCAL UINT wUtcCloseCall = 0;

```

```

_LOCAL int iStatusSizeMin;
_LOCAL BOOL bPause = FALSE;

```

```

_LOCAL HICON hicoMain;
_LOCAL HICON hicoStat;

```

```

_LOCAL HBITMAP hbmpPaint;
_LOCAL HBITMAP hbmpAnd;

```

```

_LOCAL HFONT hFontCur = NULL;
_LOCAL int cxStatusText;
_LOCAL int cyStatusText;

```

```

_LOCAL RECOGRES vrState;

```

```

/*-----
FUNCTION  _LOCAL int StatusBarPer(Rect, val)
DESCRIPTION Return pixel location of a percentage of the rectangle.
PARAMETERS LPRECT Rect - Specifies pointer to the rectangle.
            int val - Specifies value in percents.
RETURN     The pixel location of a percentage of the rectangle.
*/
_LOCAL int StatusBarPer(LPRECT Rect, int val)
{
    return(Rect->left + (int)((((LONG) val) * ((LONG)(Rect->right - Rect->left))) / 100L));
}

```

```

/*-----
FUNCTION  _LOCAL void StatusBarDraw(hDC, Rect, Min, Max, Cur, hBrush)
DESCRIPTION Draw the percentage bar for the current value.
PARAMETERS HDC hDC - Specifies target DC.
            LPRECT Rect - Specifies pointer to the rectangle.
            int Min - Specifies
            int Max - Specifies
            int Cur - Specifies
            HBRUSH hBrush - Specifies
RETURN     None.
*/
_LOCAL void StatusBarDraw(HDC hDC, LPRECT Rect, int Min, int Max, int Cur, HBRUSH
hBrush) {

```

2013-09-20 14:20:00

FOR "32260"

```
HBRUSH hBrBad;
HBRUSH hBrGood;
HANDLE hPrv;
int Maxp;
int Minp;

hBrBad = CreateSolidBrush(RGB(255, 0, 0)) ;    /* Bad range. */
hBrGood = CreateSolidBrush(RGB(0, 255, 0)) ;    /* Good range. */

hPrv = SelectObject(hDC, hBrBad) ;

Minp = StatusBarPer(Rect, Min);
if (Min)
{
    Rectangle(hDC, Rect->left, Rect->top, Minp, Rect->bottom);
}

Maxp = StatusBarPer(Rect, Max);
if (Max != 100)
{
    Rectangle(hDC, Maxp, Rect->top, Rect->right, Rect->bottom);
}

SelectObject(hDC, hBrGood) ;
Rectangle(hDC, Minp, Rect->top, Maxp, Rect->bottom);

SelectObject(hDC, hPrv);    /* restore previous selected object. */
DeleteObject(hBrGood) ;
DeleteObject(hBrBad) ;

/*
** Draw the current bar.
*/
hPrv = SelectObject(hDC, hBrush) ;

Minp = Rect->top + ((Rect->bottom - Rect->top) / 4);
Maxp = Rect->top + (((Rect->bottom - Rect->top) * 3) / 4);

Rectangle(hDC, Rect->left, Minp, StatusBarPer(Rect, Cur), Maxp);
SelectObject(hDC, hPrv);    /* restore previous selected object. */
}
```

```
/*-----
|
| FUNCTION    _LOCAL void StatusBars(hDC)
|
| DESCRIPTION Update the data changes to the status window bars.
|
| PARAMETERS HDC hDC - Specifies target DC.
|
| RETURN     None.
|
|*/
_LOCAL void StatusBars(HDC hDC)
```

{

```
RECT rc;
HBRUSH hBrush;
HANDLE hFont;
COLORREF hOldBk;
char szWork[PROMPT_LEN + 1];

if (! (UserGetFlags() & PREF_Confid) && ! (UserGetFlags() & PREF_Volume))
    return;
if (IsIconic(hwndStatus))
    return;

/*
** Get the new font.
*/
hFont = SelectObject(hDC, hFontCur);

/*
** Get the location of the status bars.
** From the client area rectangle get the rectangle for the first bar.
*/

GetClientRect(hwndStatus, (LPRECT)&rc);

DrawIcon(hDC, rc.right - GetSystemMetrics(SM_CXICON) - 2, 2, bPause ? hicoMain :
hicoStat);

rc.left = PROMPT_LEN * cxStatusText;
rc.right -= GetSystemMetrics(SM_CXICON) + 4;
rc.top = 2;
rc.bottom = cyStatusText;

/*
** Always using this brush.
*/
hBrush = CreateSolidBrush(RGB (0, 0, 255)); /* Current val */
hOldBk = SetBkColor(hDC, GetSysColor(COLOR_BTNFACE));

if (UserGetFlags() & PREF_Confid)
{
    /*
    ** The confidence display bar.
    */
    LoadString(VChInst, IDS_CONFID, (LPSTR)szWork, PROMPT_LEN);
    TextOut(hDC, cxStatusText, rc.top, szWork, lstrlen(szWork));

    StatusBarDraw(hDC, &rc, UserGetConfidence(), 100,
vrState.confidence, hBrush);

    /*
    ** Move the rectangle down.
    */
    rc.top += cyStatusText + 4;
    rc.bottom += cyStatusText + 4;
}
```

For "326260"

```

if (UserGetFlags() & PREF_Volume)
{
    /*
    ** The volume display bar.
    */
    LoadString(VChInst, IDS_VOLUME, (LPSTR)szWork, PROMPT_LEN);
    TextOut(hDC, cxStatusText, rc.top, szWork, lstrlen(szWork));

    StatusBarDraw(hDC, &rc, iVolumeMin, iVolumeMax,
        vrState.amplitude, hBrush);

    /*
    ** Move the rectangle down.
    */
    rc.top += cyStatusText + 4;
    rc.bottom += cyStatusText + 4;
}

/*
** Put the old font back.
*/
SelectObject(hDC, hFont);

/*
** Free brush.
*/
DeleteObject(hBrush);
SetBkColor(hDC, hOldBk);
}

/*-----
FUNCTION  _LOCAL void StatusChange(void)
DESCRIPTION Update status information.
PARAMETERS None.
RETURN   None.
*/
_LOCAL void StatusChange(void)
{
    HDC hDC;
    char szWork[MAXSTRING + 1];

    if (vrState.confidence >= UserGetConfidence())
    {
        StringLoadParam(szWork, IDS_NEW, (LPSTR)vrState.word[0]);
    }
    else
    {

```

```

        LoadString(VChInst, IDS_QUERY, szWork, MAXSTRING);
    }
    SetWindowText(hwndStatus, szWork);

    hDC = GetDC(hwndStatus);

    StatusBars(hDC);

    ReleaseDC(hwndStatus, hDC);
}

```

```

/*-----
FUNCTION  _LOCAL UINT PhraseFind(szStr)
DESCRIPTION Find phrase in phrase listbox
PARAMETERS PSTR szStr - Specifies pointer to the phrase.
RETURN    Index in the listbox or LB_ERR.
*/
_LOCAL UINT PhraseFind(PSTR szStr)
{
    UINT wIdx;
    LONG IRet;
    char szWord[MAX_SYMBOL_LENGTH];

    wIdx = 0;
    while (1)
    {
        IRet = SendMessage(hwndList, LB_GETTEXT, wIdx, (LONG)(LPSTR)szWord);
        if (IRet == LB_ERR || IRet == NULL)
            return((UINT)LB_ERR);
        if (! lstrcmpi(szStr, szWord))
            return(wIdx);
        wIdx++;
    }
}

```

```

/*-----
FUNCTION  _LOCAL UINT CloseCallFind(szStr)
DESCRIPTION Check phrase as a close call number.
PARAMETERS PSTR szStr - Specifies pointer to the phrase.
RETURN    Index in the listbox or LB_ERR.
*/
_LOCAL UINT CloseCallFind(PSTR szStr)
{
    UINT wIdx;
    LONG IRet;

```

F01100-00000000


```

/*-----
FUNCTION  _LOCAL int PhraseListInc(void)
DESCRIPTION Return close call list increment
PARAMETERS None.
RETURN   Close call list increment
*/
_LOCAL int PhraseListInc(void)
{
    RECT Rect;
    int ListSize;
    int CloseCallSize;

    CloseCallSize = wCloseCallNumber * (cyStatusText + 1);
    GetClientRect(hwndStatus, (LPRECT) &Rect);
    ListSize = Rect.bottom - iStatusSizeMin;
    if (ListSize < 0)
    {
        ListSize = 0;
    }
    return((ListSize >= CloseCallSize) ? 0 : CloseCallSize - ListSize);
}

/*-----
FUNCTION  BOOL PhraseListAdd(szStr, ContextEntry)
DESCRIPTION Add phrase to the phrase list.
PARAMETERS PSTR szStr    - Specifies pointer to the phrase.
              int ContextEntry - Specifies index in the context list.
RETURN     TRUE if success.
*/
BOOL PhraseListAdd(char * szStr, int ContextEntry)
{
    UINT wIdx;
    BOOL bWord = FALSE;

    if (szStr == NULL)
    {
        return(TRUE);
    }

    if (ContextEntry == -1)
    {
        /*
        ** Has no context link so look for one.
        */
        if (PhraseFind(szStr) != -1) return(TRUE);
    }
}

```

```

    }

#ifdef DEBUG_DLG
    if (DebugFlag & DEBUG_Recog)
#endif
        bWord = SpeechEnable(szStr);

    /*
    ** Now add it to the list.
    */
    wIdx = (UINT) SendMessage(hwndList, LB_ADDSTRING, 0, (DWORD)(LPSTR) szStr);
    if (wIdx == (UINT)LB_ERR)
    {
        return(FALSE);
    }
    SendMessage(hwndList, LB_SETITEMDATA, wIdx, MAKELONG(ContextEntry,
bWord));
    return(TRUE);
}

```

```

/*-----
FUNCTION  _LOCAL void PhraseListSetup(void)
DESCRIPTION Get the current set of words and give them to the recognizer.
PARAMETERS None.
RETURN    None.
*/

```

```

_LOCAL void PhraseListSetup(void)
{

```

```

    UINT wIdx;
    RECT rc;

    if (! hwndList)
        return;

```

```

    SendMessage(hwndList, WM_SETREDRAW, FALSE, 0);
    SendMessage(hwndList, LB_RESETCONTENT, 0, 0);

```

```

#ifdef DEBUG_DLG
    if (DebugFlag & DEBUG_Recog)
#endif

```

```

        SpeechDisableAll();          /* Disable all words. */

```

```

        ContextListAdd();            /* Get context first. */

```

```

    if (wCloseCallInc)
    {

```

```

        /*
        ** Resize window to normal
        */
        GetWindowRect(hwndStatus, &rc);
    }

```

0076935-02401
101120566260

```

rc.bottom -= wCloseCallInc;
wCloseCallInc = 0;
MoveWindow(
    hwndStatus,
    rc.left,
    rc.top,
    rc.right - rc.left,
    rc.bottom - rc.top,
    TRUE);
}

if (bCloseCallWas)
{
    /*
    ** Include CloseCall information
    */
    wCloseCallNumber = 0;
    for (wIdx = 0; wIdx < vrState.nWords; PhraseListMove(vrState.word[wIdx ++]));

    if (!IsIconic(hwndStatus))
    {
        /*
        ** Should we resize PhraseList ?
        */
        wCloseCallInc = PhraseListInc();
        if (wCloseCallInc) {
            GetWindowRect(hwndStatus, &rc);
            MoveWindow(
                hwndStatus,
                rc.left,
                rc.top,
                rc.right - rc.left,
                rc.bottom - rc.top + wCloseCallInc,
                TRUE);
        }
    }
}

SendMessage(hwndList, WM_SETREDRAW, TRUE, 0);

```

```

}

/*-----
FUNCTION    _LOCAL void PhraseDrawItem(LPDRAWITEMSTRUCT lpd)
DESCRIPTION Draw item routine for the status item.
PARAMETERS LPDRAWITEMSTRUCT lpd - Specifies pointer to the DRAWITEMSTRUCT.
RETURN     None.
*/
_LOCAL void PhraseDrawItem(LPDRAWITEMSTRUCT lpd)
{

```

```

HBRUSH hBrush;
int iBkColor;
int iTxColor;
char szWord[2 * MAX_SYMBOL_LENGTH + 50];

if (lpd->itemID == -1)
    return;

if ((lpd->itemState & ODS_SELECTED) && (lpd->itemState & ODS_FOCUS))
{
    iBkColor = COLOR_HIGHLIGHT;
    iTxColor = COLOR_HIGHLIGHTTEXT;
}
else
{
    iBkColor = COLOR_WINDOW;
    iTxColor = COLOR_WINDOWTEXT;
}

SetTextColor(lpdc->hDC, GetSysColor(iTxColor));
SetBkColor(lpdc->hDC, GetSysColor(iBkColor));

hBrush = CreateSolidBrush(GetSysColor(iBkColor));
FillRect(lpdc->hDC, (LPRECT)&(lpd->rcItem), hBrush);
DeleteObject(hBrush);

/*
** Now draw the text.
*/
SendMessage(hwndList, LB_GETTEXT, lpd->itemID, (LONG)(LPSTR)szWord);
if (bCloseCallWas && lpd->itemID < wCloseCallNumber)
{
    PaintBitmap(
        lpdc->hDC, lpd->rcItem.left, lpd->rcItem.top,
        BMP_SIZE, BMP_SIZE,
        hbmpAnd, hbmpPaint, lpd->itemID * BMP_SIZE, 0);
    TextOut(lpdc->hDC, lpd->rcItem.left + BMP_SIZE, lpd->rcItem.top, szWord,
        lstrlen(szWord));
}
else
{
    if (!HIWORD(SendMessage(hwndList, LB_GETITEMDATA, lpd->itemID, 0L)))
    {
        SetTextColor(lpdc->hDC, GetSysColor(COLOR_GRAYTEXT));
    }

#ifdef DEBUG_DLG
    if (DebugFlag & DEBUG_ContFull)
    {
        TabbedTextOut(lpdc->hDC, lpd->rcItem.left, lpd->rcItem.top,
            szWord, lstrlen(szWord), 2, ContextTabs, lpd->rcItem.left);
    }
    else
#endif
        TextOut(lpdc->hDC, lpd->rcItem.left, lpd->rcItem.top, szWord, lstrlen(szWord));
}

```

101120"5226260


```

int sfNew = UserGetFlags();
RECT rc;
int yInc = 0;

iStatusSizeMin = 0;
if (sfNew & PREF_Volume)
    iStatusSizeMin += 4 + cyStatusText;
if (sfNew & PREF_Confid)
    iStatusSizeMin += 4 + cyStatusText;
iStatusSizeMin = max(iStatusSizeMin, 6 + GetSystemMetrics(SM_CYICON));
GetClientRect(hwnd, &rc);
if (rc.bottom < iStatusSizeMin)
    yInc = iStatusSizeMin - rc.bottom;
GetWindowRect(hwnd, &rc);
MoveWindow(
    hwnd,
    rc.left,
    rc.top,
    rc.right - rc.left,
    rc.bottom - rc.top + yInc,
    TRUE);
SendMessage(hwnd, WM_SIZE, 0, 0L);
InvalidateRect(hwnd, NULL, TRUE) ; /* rebuild if resized or not */
ContextCheck(TRUE);
PhraseListSetup();          /* rebuild the current vocab list. */

```

```

}

```

```

/*-----

```

```

| FUNCTION _LOCAL void SelectOurFont()
|
| DESCRIPTION Select font for phrase listbox.
|
| PARAMETERS None.
|
| RETURN None.
|

```

```

*/

```

```

_LOCAL void SelectOurFont()
{

```

```

    HDC    hDC;
    TEXTMETRIC tm;
    HFONT hFontNew;

```

```

    hFontNew = UserGetFont();

```

```

    hDC = CreateIC((LPSTR)"DISPLAY", NULL, NULL, NULL) ;
    SelectObject(hDC, hFontNew) ;
    GetTextMetrics(hDC, &tm);

```

```

    SendMessage(hwndList, WM_SETFONT, hFontNew, 0L);

```

T0110"5243260


```

        SendMessage(hwndList, LB_SETITEMHEIGHT, 0, MAKELONG(max(tm.tmHeight,
BMP_SIZE), 0));
        cxStatusText = tm.tmAveCharWidth;
        cyStatusText = tm.tmHeight;
        if (hFontCur != NULL)
            DeleteObject(hFontCur);
        hFontCur = hFontNew;
        DeleteDC(hDC);
    }
}

```

```

/*-----
FUNCTION  BOOL CALLBACK StatusWndProc(hwnd, wMsg, wParam, lParam)

```

```

DESCRIPTION Window Proc VoiceStatus class.
The form of the status window is follows:
    Title bar = System menu icon, last word, w/ current
    Confidence
    Volume
    Current options list box.

```

```

PARAMETERS HWND hwnd - Specifies the handle of the window
            UINT wMsg - Specifies the message
            WORD wParam - Specifies 16 bits of additional
                        message-dependent information
            LONG lParam - Specifies 16 bits of additional
                        message-dependent information

```

```

RETURN      Depend upon the message.

```

```

*/
long FAR PASCAL StatusWndProc(HWND hwnd, UINT wMsg, WORD wParam, LONG lParam)
{

```

```

    static WORD  wMenuCmd = NULL;
    static DWORD dwMenuBits = NULL;
    static BOOL  bRecogReady = FALSE;

```

```

    switch (wMsg)
    {

```

```

        case WM_CREATE:
        {

```

```

            /* Install System
            */

```

```

            LPCREATESTRUCT lpcs = (LPCREATESTRUCT) lParam;

```

```

            /* Create the list of available words for the user.
            */

```

```

            hwndList = CreateWindow(
                "LISTBOX",
                NULL,
                WS_CHILD | WS_VISIBLE | WS_BORDER |
                WS_HSCROLL | LBS_NOINTEGRALHEIGHT |
                LBS_NOTIFY | LBS_OWNERDRAWFIXED |
                LBS_HASSTRINGS | LBS_WANTKEYBOARDINPUT,
                iStatusSizeMin,

```

101120-522520

```

        0,
        lpcs->cx - iStatusSizeMin,
        lpcs->cy,
        hwnd,
        IDLIST_PHRASE,
        VChInst,
        (LPSTR) NULL);
    if (hwndList == NULL)
    {
        return(-1);
    }

    /* Hook message queue
    */
    HookInstall(TRUE);

    /* Start DDE with Program Manager
    */
    ShellDdeInit(&VCTalk);

    /* Install help hook (F1 in dialogs and menu)
    */
    HelpHookInit();

    /* The window gets created, so do the one time stuff.
    */
    hicoMain = LoadIcon(VChInst, MAKEINTRESOURCE(ICO_MAIN));
    hicoStat = LoadIcon(VChInst, MAKEINTRESOURCE(ICO_STAT));
    hbmpPaint = LoadBitmap(VChInst,
MAKEINTRESOURCE(BMP_CLCALL));
    hbmpAnd = CreateAndBitmap(hbmpPaint);

#ifdef DEBUG_DLG
    /* Update system menu
    */
    {
        char szWork[MAXSTRING + 1];
        HMENU hMenu = GetSystemMenu(hwnd, FALSE);

        AppendMenu(hMenu, MF_SEPARATOR, 0, 0);
        LoadString(VChInst, IDS_DEBUG, (LPSTR)szWork,
MAXSTRING);
        AppendMenu(hMenu, MF_STRING, IDM_SYSDEBUG,
(LPSTR)szWork);
        DrawMenuBar(hwnd);
    }
#endif

    /* Set prefs
    */
    SelectOurFont();
    StatusSetPref(hwnd);

    /* Status is owner of the speech channel
    */
    SpeechOwner(hwnd);

```

10440"SE26260

```

        /* Set the initial values to the prase list.
        */
        PhraseListSetup();

        bRecogReady = TRUE;

        /* Do not put break here.
        ** We change user from void to current
        */
    }

case VCM_USERCHANGED:
{
    RECT rc;
    HCURSOR hcur;
    HWND hwndEdit;

    hcur = SetCursor(LoadCursor(NULL, IDC_WAIT));

    /* Set Status placement
    */
    UserGetWinRect(szStatusClass, &rc);
    MoveWindow(
        hwnd,
        rc.left,
        rc.top,
        rc.right - rc.left,
        rc.bottom - rc.top,
        TRUE);
    StopTimer();
    bRecogReady = FALSE;

    /* Load voice file
    */
#ifdef DEBUG_DLG
    if (DebugFlag & DEBUG_Recog)
#endif
        SpeechUserChange();

    /* Load Language
    */
    hwndEdit = FindWindow(szFrameClass, NULL);
    if (hwndEdit != NULL)
    {
        /* Load from the editor
        */
        ContextNewLang((LPLANG)SendMessage(hwndEdit,
iEditChangeMsg, 0, 0L));
    }
    else
    {
        /* Load from the file
        */
        ContextNewLang(NULL);
    }
}

```

092326260

```

        bRecogReady = TRUE;
        StartTimer();
        SetCursor(hcur);
        PhraseListSetup();
        break;
    }

    case WM_MENUSELECT:
        /* Keep menu selection for help
        */
        dwMenuBits=lParam;
        wMenuCmd=wParam;
        goto defmsg;

    case VCM_HELP:
        if (!(LOWORD(dwMenuBits) & MF_POPUP))
        {
            if (!(LOWORD(dwMenuBits) & MF_SYSMENU))
            {
                /* Menu help
                */
                Help(hwnd, HELP_VCMMenuPrefs + wMenuCmd -
MENU_STATUS);
            }
            else
            {
                /* System menu help
                */
                Help(hwnd, HELP_SysMenu);
            }
        }
        else
        {
            /* General help
            */
            Help(hwnd, HELP_Status);
        }
        break;

    case VCM_SPEECH:
    {
        /*
        ** Speech available
        */
        UINT wIdx;
        UINT wUtt;

        if (bRecogReady && !bPause)
        {
            bRecogReady = FALSE;
            StopTimer();
            wUtt = SpeechRecog(&vrState);

            /* Check Close Call list first.

```

104120-50200


```

        if (!HIWORD(IData)) {
            SendMessage(hwndList, LB_SETITEMDATA, wIdx,
MAKELONG(LOWORD(IData), TRUE));
            SendMessage(hwndList, LB_GETITEMRECT, wIdx,
(LONG)(LPRECT)&rc);
            InvalidateRect(hwndList, &rc, TRUE);
        }
    }
}

```

```

    }
    break;
}

```

```
case WM_PAINT:
```

```

{
    /* A repaint instruction has been given.
    */
    HDC      hDC;
    PAINTSTRUCT ps;
    HICON     hIcon;

    hDC = BeginPaint(hwndStatus, (LPPAINTSTRUCT)&ps);
    if (IsIconic(hwndStatus))
    {
        /* Draw iconic window
        */
        hIcon = (bPause) ? hicoMain : hicoStat;
        DrawIcon(hDC, 0, 0, hIcon);
    }
    else
    {
        /* Create the volume and confidence boxes.
        */
        StatusBars(hDC);
    }
    EndPaint(hwndStatus, (LPPAINTSTRUCT)&ps);
    break;
}

```

case WM_SIZE:

```
{
    /* Move the phrase list.
    */
    RECT rc;

    GetClientRect(hwnd, &rc);
    MoveWindow(
        hwndList,
        rc.left,
        rc.top + iStatusSizeMin,
        rc.right - rc.left + 1,
        rc.bottom - rc.top - iStatusSizeMin + 1,
        TRUE);

    break;
}
```

case WM_GETMINMAXINFO:

1

```

MINMAXINFO FAR * lpmmi = (MINMAXINFO FAR *) lParam;
RECT rc;

memset(&rc, 0, sizeof(rc));
rc.bottom = iStatusSizeMin;
AdjustWindowRect(&rc, WS_OVERLAPPEDWINDOW, TRUE);

lpmmi->ptMinTrackSize.x = MAX_SYMBOL_LENGTH * cxStatusText;
lpmmi->ptMinTrackSize.y = rc.bottom - rc.top + wCloseCallInc;
break;

```

```

}

```

```

case WM_SETFOCUS:
    /* We just got the focus.
    */
    SetFocus(hwndList);          /* Give it to the list box. */
    break;

```

```

case WM_QUERYDRAGICON:
    /* A repaint instruction has been given.
    */
    return(bPause ? hicoMain : hicoStat);

```

```

case WM_DRAWITEM:
    /* The system listbox wants us to draw the item.
    ** DRAWITEMSTRUCT
    */
    PhraseDrawItem((LPDRAWITEMSTRUCT) lParam);
    break;

```

```

#ifdef DEBUG_DLG

```

```

    case WM_SYSCOMMAND:
        if ((wParam & 0xFFFF) == IDM_SYSDEBUG)
        {
            /* Bring up the Debug dialog box.
            */
            DialogBox(VChInst, MAKEINTRESOURCE(DLG_DEBUG),
                hwnd, DebugDlgProc);

            /* Rebuild phrase list
            */
            PhraseListSetup();
        }
        else
        {
            goto defmsg;
        }
        break;

```

```

#endif

```

```

case WM_COMMAND:
    switch (wParam)
    {
        case IDM_PREFS:
            /* Bring up the User Preferences dialog box.

```

T01F20" 52Z3200


```

case IDM_HELPSEARCH:
    /* Bring up the Help Search
    */
    Help(hwnd, HELP_Search);
    break;

case IDM_HELPONHELP:
    /* Bring up the HelpOnHelp
    */
    Help(hwnd, HELP_OnHelp);
    break;

case IDM_ABOUT:
    /* Bring up the About.. dialog box.
    */
    About(hwnd);
    break;

case IDLIST_PHRASE:
    switch (HIWORD(lParam)) {
        case LBN_DBLCLK:

#ifdef DEBUG_DLG
            (UINT)SendMessage(hwndList, LB_GETCURSEL, 0, 0);

            LB_GETTEXT, widx, (LONG)(LPSTR)(vrState.word[0]));
            DEBUG_ContFull)

            information

            vrState.word[0]; *Ptr, Ptr++)

            '\0';

#endif

            if (DebugFlag & DEBUG_Force) {
                /* Execute command
                */
                char * Ptr;
                UINT widx =

                vrState.confidence = 100;
                vrState.amplitude = 0;
                SendMessage(hwndList,

                if (DebugFlag &

                {
                    /* Skip debug

                    */
                    for (Ptr =

                    {
                        if (*Ptr == '\t')
                        {
                            *Ptr =

                            break;

                        }

                    }

                }
                PhraseExec(widx);
                break;

            }

            /* Train command
            */

```

1000-0000-0000-0000-0000-0000-0000-0000


```

    {
        /* Free resores
        */
        HCURSOR hcur;

        hcur = SetCursor(LoadCursor(NULL, IDC_WAIT));
        StopTimer();
        DestroyIcon(hicoStat);
        DestroyIcon(hicoMain);
        DeleteObject(hbmpPaint);
        DeleteObject(hbmpAnd);
        DeleteObject(hFontCur);

        /* Free speech system
        */

#ifdef DEBUG_DLG
        if (DebugFlag & DEBUG_Recog)
#endif
            SpeechFree();

        /* Unhook message queue
        */
        HookInstall(FALSE);
        HookFreeJournal();

        /* Close help if was opened
        */
        Help(hwnd, HELP_Quit);

        /* Stop DDE
        */
        ShellDdeExit(&VCTalk);

        /* Unhook help hook
        */
        HelpHookExit();

        /* Save the user file.
        */
        UserExit();
        SetCursor(hcur);

        /* Kill the task and other windows.
        */
        PostQuitMessage(0);
        break;
    }
    default:
        if (wMsg == iEditChangeMsg)
        {
            /* Changes in Editor saved
            ** We need to update language
            */
            HCURSOR hcur;

```

```

hcur = SetCursor(LoadCursor(NULL, IDC_WAIT));
StopTimer();
bRecogReady = FALSE;

```

```

/* Load Language
*/
ContextNewLang((LPLANG)IParam);
bRecogReady = TRUE;
StartTimer();
SetCursor(hcur);
break;
}

```

```

defmsg:
return DefWindowProc(hwnd, wMsg, wParam, lParam);
}

```

```

return (NULL);
}

```

```

/*-----
FUNCTION  BOOL StatusInit(BOOL bNew)
DESCRIPTION
PARAMETERS
RETURN
*/
BOOL StatusInit(BOOL bNew)
{

```

```

WNDCLASS wc;
char  szTitle[MAXSTRING + 1];
RECT  rc;
HWND  hwnd;

```

```

if (bNew)
{

```

```

    UserInit();

```

```

    /* To reload file
    */

```

```

    iEditChangeMsg = RegisterWindowMessage(szFrameClass);

```

```

    /* Register the window class.
    */

```

```

    memset(&wc, 0, sizeof(wc));          /* zero structure to start. */

```

```

    wc.style      = CS_DBLCLKS | CS_HREDRAW | CS_VREDRAW ;
    wc.lpfnWndProc = (WNDPROC)StatusWndProc;
    wc.hInstance  = VChInst;              /* task owner. */
    wc.hCursor    = LoadCursor(NULL, IDC_ARROW) ;

```

101100 5226260

```

wc.hbrBackground = COLOR_BTNFACE + 1;
wc.lpszClassName = (LPSTR) szStatusClass;
wc.lpszMenuName = MAKEINTRESOURCE(MENU_STATUS);

if (! RegisterClass(&wc))
    return(FALSE);

hAccTableStatus = LoadAccelerators(VChInst,
MAKEINTRESOURCE(ATBL_STATUS));

/* Create Status Window
*/
UserGetWinRect(szStatusClass, &rc);
LoadString(VChInst, IDS_TITLE, (LPSTR)szTitle, sizeof(szTitle) - 1);

hwndStatus = CreateWindowEx(
    WS_EX_TOPMOST,
    szStatusClass,
    (LPSTR)szTitle,
    WS_OVERLAPPEDWINDOW & (~WS_MAXIMIZEBOX),
    rc.left,
    rc.top,
    rc.right - rc.left,
    rc.bottom - rc.top,
    NULL,
    NULL,
    VChInst,
    (LPSTR) NULL);

if (! hwndStatus)
    return(FALSE);

/* Send timer message to update context.
** every 1/2 of a second or so.
*/
StartTimer();
ShowWindow(hwndStatus, SW_SHOWNORMAL);

/* Install recognition system
*/
#ifdef DEBUG_DLG
    if (DebugFlag & DEBUG_Recog)
        SpeechInit();

        PhraseListSetup();
    }
else
    {
        /* Only one instance of Voice Control should be present
        */
        hwnd = FindWindow(szStatusClass, NULL);
        if (hwnd)
        {
            /* This should always be true !?

```

```
*/  
ShowWindow(hwnd, SW_SHOWNORMAL);
```

```
/* Flash it to indicate location.
```

```
*/  
SetFocus(hwnd);  
}  
}  
  
return(TRUE);  
}  
  
/*-----  
FUNCTION  BOOL StatusCheckMsg(MSG * pMsg)  
DESCRIPTION Message translation.  
PARAMETERS MSG * pMsg - Specifies pointer to the incoming message.  
RETURN    TRUE if processed(message belong to the status).  
*/  
BOOL StatusCheckMsg(MSG * pMsg)  
{  
  
    if (hwndStatus != NULL && GetFocus() == hwndList &&  
        TranslateAccelerator(hwndStatus, hAccTableStatus, pMsg))  
        return(TRUE);  
  
    return(FALSE);  
}  
  
/*-----  
FUNCTION  HWND StatusGetWindow(void)  
DESCRIPTION Return status window handle.  
PARAMETERS None.  
RETURN    Window handle.  
*/  
HWND StatusGetWindow(void)  
{  
    return(hwndStatus);  
}
```

009325-0110
104120-5226260